NPS-67-84-008

NAVAL POSTGRADUATE SCHOOL
Monterey, California

THESIS

GROUND-UP-TO-SPACE (GUTS)
LASER PROPGATION CODE
DESCRIPTION AND MANUAL

by

Joel Steven Morrow

June 1984

Thesis Advisor: A. E. Fuhs

Approved for public release; distribution unlimited

Prepared for: Dr. Fred Raymond, Code 9110
Naval Research Laboratory
4555 Overlook Ave., SW
Washington, D.C. 20375

NAVAL POSTGRADUATE SCHOOL

Monterey, California

Commodore R. H. Shumaker
Superintendent

David Schrady
Provost

This thesis prepared in conjunction with research supported in part by the Naval Research Laboratory, Washington, D.C.

Released as a
Technical Report by:

REPORT DOCUMENTATION PAGE

READ INSTRUCTIONS BEFORE COMPLETING FORM

1. REPORT NUMBER
NPS 67-84-008

2. GOVT ACCESSION NO.

3. RECIPIENT'S CATALOG NUMBER

4. TITLE (and Subtitle)
Ground-Up-to-Space (GUTS) Laser Propagation Code Description and Manual

5. TYPE OF REPORT & PERIOD COVERED
Master's Thesis
June 1984

6. PERFORMING ORG. REPORT NUMBER

7. AUTHOR(s)
Joel Steven Morrow

8. CONTRACT OR GRANT NUMBER(s)
N0001484WRP4012

9. PERFORMING ORGANIZATION NAME AND ADDRESS
Naval Postgraduate School
Monterey, California, 93943

10. PROGRAM ELEMENT, PROJECT, TASK AREA & WORK UNIT NUMBERS

11. CONTROLLING OFFICE NAME AND ADDRESS
Naval Postgraduate School
Monterey, California, 93943

12. REPORT DATE
June 1984

13. NUMBER OF PAGES
141

14. MONITORING AGENCY NAME & ADDRESS (if different from Controlling Office)
Dr. Fred Raymond
Naval Research Laboratory
4555 Overlook Ave. SW
Washington, D.C. 20375

15. SECURITY CLASS. (of this report)
Unclassified

15a. DECLASSIFICATION/DOWNGRADING SCHEDULE

16. DISTRIBUTION STATEMENT (of this Report)
Approved for public release; distribution unlimited

17. DISTRIBUTION STATEMENT (of the abstract entered in Block 20, if different from Report)

18. SUPPLEMENTARY NOTES

19. KEY WORDS (Continue on reverse side if necessary and identify by block number)
High Energy Laser
Laser Propagation
Laser Weapon Simulation Program
ASAT Laser Simulation

20. ABSTRACT (Continue on reverse side if necessary and identify by block number)

GUTSAVG is a high energy laser propagation program for ground-to-space applications. Written by Dr. C. B. Hogge from the Air Force Weapons Laboratory, Kirtland AFB, it is one in a family of propagation codes addressing this application. Specifically, GUTSAVG was designed to compute irradiance at the target given a model atmosphere, laser device parameters, and simple target engagement geometry. The transmitter induced

effects of beam quality and jitter are considered as are the linear atmospheric effects of scattering, absorption, and turbulence. A thermal blooming model is also included. Adaptive optics compensation can be applied with consideration given to isoplanatic effects.

Ground-Up-to-Space (GUTS)
Laser Propagation Code
Description and Manual

by

Joel S. Morrow
Lieutenant, United States Navy
B.S., University of South Carolina, 1976

Submitted in partial fulfillment of the
requirements for the degree of

MASTER OF SCIENCE IN AERONAUTICAL ENGINEERING

from the

NAVAL POSTGRADUATE SCHOOL
June 1984

ABSTRACT

GUTSAVG is a high energy laser propagation computer program for ground-to-space applications. Written by Dr. C. E. Hogge from the Air Force Weapons Laboratory, Kirtland AFB, it is one in a family of propagation codes addressing this application. Specifically, GUTSAVG was designed to compute irradiance at the target given a model atmosphere, laser device parameters, and simple target engagement geometry. The transmitter induced effects of beam quality and jitter are considered as are the linear atmospheric effects of scattering, absorption, and turbulence. A thermal blooming model is also included. Adaptive optics compensation can be applied with consideration given to isoplanatic effects.

TABLE OF CONTENTS

LIST OF TABLES

LIST OF FIGURES

I. INTRODUCTION

GUTSAVG is a simplified laser propagation program. It is intended specifically for near vertical ground-to-space applications utilizing a fixed earth-based transmitter directed at a single target satellite. The primary purpose of the program is to provide irradiance and fluence on target along with related propagation data.

The program was written by Charles B. Hogge from the Air Force Weapons Laboratory, Kirtland Air Force Base, Albuquerque, New Mexico. GUTSAVG is one of a family of ground-to-space propagation programs. Other versions include GUTSFP (footprint) and GUTSMTF. GUTSFP computes an engagement envelope based on user supplied irradiance threshold levels. The propagation calculation methods are identical to GUTSAVG. GUTSMTF is a full wave-optics program using fast Fourier transforms in the beam propagation computations.

The basic approach used in GUTSAVG is to utilize modulation transfer functions to characterize effects such as beam quality, jitter, turbulence and to apply these effects at the aperture as a single phase screen. The same approach is used in ESP-IV [Ref. 1]. The general modulation transfer function, (MTF), used in this way is described in following sections along with the development of each beam degrading mechanism. A linearized model is used for thermal blooming which is also effectively applied at the aperture as a phase screen. In the case of blooming, however, the phase variance due to blooming is computed, and the Strehl relation is used to determine the relative irradiance reduction. The effect of thermal blooming and the other spreading effects are combined using both RSS and multiplicative methods. Finally, the average of these two methods is used to determine the

total system irradiance reduction from the diffraction limited case.

II. PROPAGATION FEATURES

A. THE MTF APPROACH

GLTSAVG uses MTFs to apply and then to consolidate the effects of jitter, beam quality, and turbulence. Essentially, these effects are replaced by a phase screen at the aperture which multiplies the initial complex aperture distribution by a random phase distortion factor.

Lutomirski and Yura [Ref. 2] have developed an expression for the average intensity at a point P in the far-field due to perturbations at the aperture. The intensity at P is

$$I(\overline{p}) = \left(\frac{k}{2\pi z}\right)^2 \int M_{\phi}(\overline{\rho}, z) \exp\left[-\left(\frac{i \cdot k}{z}\right)\overline{p}\,\overline{\rho}\right] d^2\overline{\rho} + \int U(r+\tfrac{1}{2}\overline{\rho})\, U^*(r-\tfrac{1}{2}\overline{\rho}) \exp\left[-\left(\frac{i \cdot k}{z}\right) r\overline{\rho}\right] d^2 r \tag{2.1}$$

where

$$\overline{\rho} = |r_2 - r_1| \tag{2.2}$$

and

$$r = \frac{r_2 + r_1}{2} \tag{2.3}$$

$\overline{p}$ is the vector from the z axis of symmetry in the far-field to the point P. $U(r)$ is the aperture distribution and $M_{\phi}(\overline{\rho}, z)$ is the MTF for the disturbance. r_1 and r_2 are two arbitrary points in the aperture where the phase perturbation is measured. $\overline{\rho}$ is the distance between the points. z, in the

case considered here, is a constant. If the phase disturbance is a random Gaussian variable with a known correlation function, then the MTF can be expressed as

$$M_\phi(\bar{\rho}) = \langle \exp[i(r_1 - r_2)] \rangle \qquad (2.4)$$

In terms of the structure function,

$$M_\phi(\bar{\rho}) = \exp\left[(-\tfrac{1}{2}) D_\phi(r_1 - r_2)\right] \qquad (2.5)$$

The second integral in equation 2.1 represents the unnormalized aperture MTF. Normalizing this term with the power in the aperture, (P_0), to cause the MTF to be unity at the origin results in

$$I(\bar{p}) = \left(\frac{k}{2\pi z}\right)^2 P_0 \int M_\phi(\bar{\rho}) M_a(\bar{\rho}) e^{-[ik\bar{\rho}\bar{p}]} d\bar{\rho}^2 \qquad (2.6)$$

Noting the symmetry of the intensity for a given p and expressing $M_\phi(\rho)$ as the combined effects of jitter, beam quality, and turbulence, equation 2.6 can be rewritten as

$$I(\bar{p}) = \left(\frac{k}{2\pi z}\right) P_0 \int M_j(\bar{\rho}) M_t(\bar{\rho}) M_b(\bar{\rho}) M_a(\bar{\rho}) J_0\left(\frac{k\bar{\rho}\bar{p}}{z}\right) \bar{\rho} d\bar{\rho} \qquad (2.7)$$

A Fourier-Bessel transform has been used. Note that the MTFs of jitter (M_j), beam quality (M_b), and turbulence (M_t) have been substituted for M_ϕ.

The ESP-IV manual [Ref. 3] contains the development above in more detail. MTFs for the specific effects are described in following sections.

E. THERMAL BLOOMING

The thermal blooming model in GUTSAVG is based on the following linearized density perturbation equation.

$$\frac{\Delta\rho}{\rho_0} = \frac{\alpha(\ell)}{V_0}\,\frac{\gamma-1}{\gamma}\,\frac{1}{p_0}\int_{-\infty}^{x'} I(x',y)\,dx' \times \exp\left[-\int\left[\alpha(\ell)+\sigma(\ell)\right]d\ell\right] \tag{2.8}$$

Here, $\alpha(\ell)$ is the atmospheric absorption coefficient at a distance ℓ along the beam, V_0 is a constant transverse wind velocity, and p_0 is the ambient pressure. The exponential term represents the total extinction due to scattering and absorption. $x'$is a constant of integration. It is assumed that the beam is propagated in the positive z direction a distance ℓ and that the wind vector is in the positive x direction. The intensity integral represents the heating of the atmosphere as it transits the beam [Ref. 4]. Some assumptions embodied in the above equation are that $V_0 << c_0$, the local sonic velocity, so that the process represented occurs at constant pressure, and that the kinetics of absorption and conversion to heat are extremely fast [Ref. 5].

By applying the Gladstone-Dale relation,the density relation can be expressed as a change in the refractive index.

$$\Delta n = (n_0-1)\frac{\Delta\rho}{\rho_0} \tag{2.9}$$

Equation 2.8 can be rewritten as

$$\Delta n = (n_0-1)\frac{\alpha(\ell)}{V_0}\;\frac{\gamma-1}{\gamma}\;\frac{1}{p_0}\int_{\infty}^{x'} I(x',y)\,dx' \times \exp\left[-\int[\alpha(\ell)+\sigma(\ell)]\,d\ell\right] \tag{2.10}$$

The change in the wavefront phase of a beam due to the refractive index charge when the beam is propagated a distance ℓ, is given by

$$\Delta\phi = \frac{2\pi}{\lambda}\int_0^{\ell} \Delta n\, d\ell \tag{2.11}$$

Substituting equation 2.10 into 2.11 and changing the limits of integration to reflect the ground-to-space propagation path results in

$$\Delta\phi(x,y) = \left[\frac{2\pi}{\lambda}\;\frac{n_0-1}{p_0}\;\frac{\gamma-1}{\gamma}\int_{-\infty}^{x'} I(x',y)\,dx'\right] \times \int_{h_t}^{h_{atm}} \frac{\alpha(h)\exp\left[-\sec\theta\int_{h_t}^{h}[\alpha(h)+\sigma(h)]\,dh\right]}{V_0\cos\xi + \omega h}\,dh \tag{2.12}$$

h_{atm} is the extent of the atmosphere, which is about about 30 km, and h_t is the height of the laser transmitter. Also, the wind term has been expanded to include the relative wind velocity due to slewing. V_0 is assumed to be parallel and opposite in direction of that of the target motion. ξ is the angle of incidence of the wind to the beam so that $V_0\cos(\xi)$ represents the transverse wind. ωh is the effective wind generated by slewing. ω is the angular slew rate.

The first portion of equation 2.12 is independent of path while the second part is not, assuming I(x,y) does not change along the propagation path. This assumption is valid only for a very small amount of blooming. The approach used

in GUTSAVG is to determine the phase distortion due to thermal blooming by first evaluating the path invariant part of equation 2.12 . This is accomplished by constructing a phase screen at the aperture and then removing the best fit tilt, focus curvature, and mean phase. Zernike polynomials are used to model these aberrations. The result is the residual phase due to thermal blooming alone. The variance of the phase is then computed.

The path dependent term is evaluated within the angle interval loop of the program and is applied to the previously computed phase variance during each path iteration. The path iteration process is diagrammed in the engagement geometry section. Also, see Figures 2.1 and 2.2 for a flow diagram of the general treatment of thermal blooming in the program.

Once the total phase variance has been determined, the Strehl relation is used to compute the intensity degradation due to thermal blooming.

$$\frac{I}{I_0} = \exp(-\sigma^2) \tag{2.13}$$

The result of equation 2.13 is a relative intensity (Irel) ratio. I_0 is the ideal on-axis irradiance with no phase distortion. The Strehl relation above is thought to be too severe a model for Irel below 0.3 [Ref. 6]. For that reason, if σ^2 is less than 1.2 , the Irel will be computed using polynomial curve fits developed from GUTSMTF results. GUTSMTF is a full wave optics code utilizing fast Fourier transforms. For a description of the curve fit method above, see the subroutine BLOOM explanation. [Ref. 7]

Combining the thermal blooming effect with the other effects, such as turbulence and jitter, is accomplished by averaging the results of two different approaches. The first

approach is the RSS (root sum squared) method. This method of combining the Irel due to the effects of thermal blooming with the Irel due to jitter, beam quality, and turbulence is accomplished as follows

$$Irel_{rss} = \left(1 + \left[\frac{1}{Irel_{tb}} - 1\right] + \left[\frac{1}{Irel_{o}} - 1\right]\right)^{-1} \quad (2.14)$$

where $Irel_{tb}$ is the thermal blooming result and $Irel_{o}$ is the result of the other effects. The second approach is a multiplicative approach and is simply

$$Irel_{m} = Irel_{o} \times Irel_{tb} \quad (2.15)$$

The two combined Irels obtained by these methods are then averaged to give the total intensity ratio due to all the attenuating or distorting propagation effects.

$$\frac{I}{I_0} = Irel_{tot} = \frac{Irel_{m} + Irel_{rss}}{2} \quad (2.16)$$

I_0 is the ideal diffraction limited on-axis intensity. The bases for the above averaging process is empirical in nature and is an attempt to adjust the results obtained by the RSS method alone. The results produced by RSS were thought to be too optimistic. The multiplicative method, a more pessimistic approach, was therefore included. The ultimate Irels obtained are very close to those obtained by GUTSMTF, the full wave code. [Ref. 8]

There are some limitations to the thermal blooming model used in GUTSAVG in addition to the assumptions already mentioned. First, the wind (V_0) is applied as a constant

everywhere in the atmosphere. At higher altitudes, this is not a major consideration due to the higher relative velocity of the beam. At low to medium altitudes this could affect thermal blooming to an extent to warrant the addition of a wind profile as a function of altitude. This could be done with little effort if the data is available. Also, the program assumes a wind parallel and opposite to the direction of the target motion. This precludes the case of slewing with the wind and the creation of null spots. Transonic blooming, which violates one of the original assumptions of the equation used, is not considered [Ref. 9]. For very low altitude satellites, the high slew rates generated would result in a supersonic relative wind across the beam. In this case, the constant pressure assumption is invalid [Ref. 10]. Kinetic cooling and molecular breakdown are also not addressed in GUTSAVG.

C. SCATTERING AND ABSORPTION

GUTSAVG does not contain any type of atmospheric model with respect to scattering and absorption data. Extinction coefficients must be entered by the user in the appropriate subroutines, ALFS and ALFA, or the program can be modified to accept a separate data file. Once inserted into the program, scattering and absorption coefficients are treated without distinction between aerosol and molecular mechanisms. Therefore, the coefficients used must represent the total effect of scattering or absorption.

$$\alpha(h) = \alpha(h)_{mol} + \alpha(h)_{aer} \tag{2.17}$$

$$\sigma(h) = \sigma(h)_{mol} + \sigma(h)_{aer} \tag{2.18}$$

Transmission due to scattering and absorption are computed indentically and given by

$$T_a = \exp\left(-\sec\theta \int_{h_t}^{h_{atm}} \alpha(h)\,dh\right) \tag{2.19}$$

where θ is the zenith angle, and the integration limits are the altitude of the transmitter and the vertical extent of the atmosphere. The extent of the atmosphere in the program is defined as 30 km. Figure 2.3 shows the program application of scattering and absorption.

D. BEAM QUALITY

GUTSAVG allows the user to describe the beam at the aperture in terms of the electromagnetic field amplitude distribution and total beam quality. The intital amplitude field used by the program is Gaussian in shape with the user specifying a waist diameter. The waist diameter is defined by the $1/e^2$ point on the distribution. Truncation of the this Gaussian field will of course depend on the aperture diameter and the size of the central obscuration. If the waist diameter is made large compared to the aperture, a more uniform distribution results.

Beam quality at the aperture exit may be specified by two different parameters. One of these is the 'times diffraction limited number', N. N has been used in a general way to mean an increase in far-field spot size or as a 'power-in-the-bucket' ratio. In GUTAVG, N is a total beam quality term. The second beam quality parameter is a nondimensional term representing the RMS phase distortion at the laser wavelength at the exit aperture, $\frac{\delta_{rms}}{\lambda}$.

The parameters are related to each other and to the intensity degradation by

$$\frac{I}{I_0} = \frac{1}{N^2} = \exp -\left(\frac{2\pi\delta_{rms}}{\lambda}\right)^2 \qquad (2.20)$$

To apply beam quality to the propagation problem, an MTF array is constructed representing a phase screen at the aperture. The phase is assumed to be a Gaussian random variable with a zero mean value. For the axi-symmetric beam considered in GUIAVG, the MTF is [Ref. 11]

$$M_b(\bar{\rho}) = \exp\left(-k^2\left[\sigma^2 - C_\phi(\bar{\rho})\right]\right) \qquad (2.21)$$

C_ϕ is the autocorrelation function of the phase and is defined as

$$C_\phi(\bar{\rho}) = \sigma^2 \exp\left[-\left(\frac{\bar{\rho}}{L}\right)^2\right] \qquad (2.22)$$

where σ^2 is the phase variance, $\left(\frac{2\pi\delta_{rms}}{\lambda}\right)^2$, and L is the phase correlation length [Ref. 12]. The beam quality MTF array is combined with the MTF arrays due to other propagation effects to determine the complete system MTF and, hence, the total irradiance degradation. Based on the provided input parameter, Figure 2.4 shows the general treatment of beam quality within the program.

E. TURBULENCE

GUISAVG uses the Hufnagel model [Ref. 13] for C_n^2 as an indicator of the optical effects of turbulence along the propagation path. C_n^2 is the refractive index structure constant and represents the refractive index in the

atmosphere as a function of turbulence induced density fluctuations. The model is an empirically derived vertical profile of C_n^2.

Fried [Ref. 14] has developed a parameter which is directly related to the behavior of a coherent beam in a turbulent medium. This term is called the effective coherence diameter, r_0. In the case of a laser transmiter, r_0 represents a physical limit to the transmitter diameter of a near diffraction-limited beam. For a transmitter diameter, D, larger than r_0, degradation of the beam by turbulence will occur. If D is smaller than r_0, then near diffraction-limited propagation will be achieved. Beam wander or pure tilt occurs for transmitter diameters approximately equal to r_0. Yura [Ref. 15] has defined a somewhat different but related term that can be thought of as a lateral coherence length, ρ_0. These two quantities are given by

$$r_0 = \left[\frac{2.19}{6.88} k^2 \sec\theta \int C_n^2(h)\ dh\right]^{-3/5} \tag{2.23}$$

and

$$\rho_0 = \left[1.45\ k^2 \sec\theta \int C_n^2(h)\ dh\right]^{-3/5} \tag{2.24}$$

so that

$$\rho_0 = \frac{r_0}{2.1} \tag{2.25}$$

where $k = \frac{2\pi}{\lambda}$, θ is the zenith angle, and the limits of integration are h_{atm}, the vertical extent of the atmosphere, and h_t, the height of the transmitter.

ρ_0 may be specified by the user as a program input or the program may be allowed to compute it based on equation 2.24 . The user may also input ρ_0 indirectly by specifying the 'seeing conditions' , a quantity used by astronomers to describe angular spread of a stellar point source (see input section and Figure 2.5). The program uses ρ_0 to compute the atmospheric MTF.

The MTF of the turbulent atmosphere is determined by developing the structure function of the turbulence. This development is demonstrated by Yura [Ref. 16]. The resulting MTF is given by

$$M_t(\bar{\rho}) = \exp\left[-\left(\frac{\bar{\rho}}{\rho_0}\right)^{3/5}\right] \tag{2.26}$$

This MTF effectively applies the the effect of turbulence along the propagation path as a phase screen at the aperture.

F. JITTER

Beam jitter is a user input and is specified by the variance of the angular excursions of the beam. Using the 2-sigma-p definition,

$$2\sigma_p = \sqrt{2(\sigma_x^2 + \sigma_y^2)} \tag{2.27}$$

where σ_x and σ_y are the axial variances of the jittered beam center in the far-field. σ_x and σ_y are random variables with Gaussian distribution and in the symmetric case , as considered by GUTSAVG, $\sigma_x = \sigma_y$. The resultant intensity distribution due to jitter will also be a Gaussian distribution with $(2\sigma_p)$ representing the spot radius defined at the $1/e^2$ point. In other words, 86.5% of the beam energy will reside within the radius $2\sigma_p$. [Ref. 17]

Jitter can be shown to be a wavefront tilt at the aperture. Using this approach, a phase screen at the aperture can be used to characterize the effects of jitter and a jitter MTF developed. That MTF is given by

$$M_j(\overline{\rho}) = \exp\left[\frac{-k^2\overline{\rho}^2(2\sigma_p)^2}{8}\right] \tag{2.28}$$

Figure 2.6 is a general flow diagram for the treatment of jitter within the program.

G. ADAPTIVE OPTICS

The ability to apply adaptive optics corrections to the propagation problem has been included in GUTSAVG. The user has several options with respect to the type and degree of compensation desired. The following general discussion and figure 2.8 provides the needed insight to the effects of selecting the adaptive optics options.

The major compensation mode provided by the program is invoked by selecting full zonal adaptive optics with consideration given to isoplanatic effects. When selected, this model results in the correction of beam degradation due to turbulence. This is accomplished by correcting turbulence induced tilt and then adjusting ρ_0 so as to produce a predetermined level of adaptive optics performance. This predetermined performance is as measured by the Strehl ratio given a residual phase variance determined by the adaptive optics sensor phase. Parameters determining the phase error are the response bandwidth of the adaptive optics system, the number of system actuaters, the reflected radiant intensity of the target, and the target-to-sensor transmission. The resultant ρ_0 found in this manner is then used to compute the atmospheric MTF. When this 'corrected' MTF is used to compute the far-field intensity, the result will represent an adaptive optics corrected value.

Without invoking full zonal adaptive optics, the user may apply a tilt-only correction for turbulence. In this case some or all of the tilt due to turbulence may be removed before computing the atmospheric MTF. The degree of tilt compensation is specified by the user.

As mentioned above, isoplanatic effects are included in the adaptive optics calculations. This is also an option, however, and isoplanatic calculations may be inhibited by the user. The effect considered is the limitation of the adaptive optics system given an isoplanatic angle smaller than the target lead angle. Fried [Ref. 18] provides a discussion of isoplanatism and development of the isoplanatic angle.

Although adaptive optics compensation for thermal blooming is not modeled in a strict sense, a thermal blooming correction factor can be applied. This factor is simply a fractional constant that multiplies the thermal blooming phase variance before the Strehl relation is used to compute the intensity degradation.

Refer to the input definitions and the subroutines involved with adaptive optics. In addition, refer to figure 2.7 for more explanation.



Figure 2.1 GLTSAVG Thermal Blooming Algorithm.



Figure 2.2 Thermal Blooming Algorithm (cont).



Figure 2.3 GUISAVG Scattering and Absorption Algorithm.



Figure 2.4 GUISAVG Beam Quality Algorithm.



Figure 2.5 GUTSAVG Turbulence Algorithm.



Figure 2.6 GUTSAVG Jitter Algorithm.



Figure 2.7 GLISAVG Adaptive optics Algorithm.



Figure 2.8 GUTSAVG Adaptive Optics Algorithm (cont).



Figure 2.9 GUTSAVG Adaptive Optics Algorithm (cont).



Figure 2.10 GUTSAVG Adaptive Optics Algorithm (cont).



Figure 2.11 GUTSAVG Adaptive Optics Algorithm (cont).



Figure 2.12 GUTSAVG Adaptive Optics Algorithm (cont).

III. PROGRAM AND SUBPROGRAM DESCRIPTION

A. PROGRAM INPUTS

The following are the inputs necessary to utilize GUTSAVG. Default values are indicated for parameters not absolutely required for program operation. At NPS these input parameters are entered via an input file. A copy of this file is provided in Appendix A. (*) indicates a nondimensional parameter.

- DIA (meters)

The diameter of the transmitter aperture.

- DIAOBS (meters)

The diameter of the central obscuration of the transmitter.

- BEAMSZ (meters)

The Gaussian waist diameter of the amplitude distribution at the aperture. (measured at the $1/e^2$ point)

- WAVE (meters)

The laser wavelength.

- PTOTAL (Watts)

The total power at the aperture.

• TDFLMT (*)

This is the often used "times diffraction limited number" and represents total beam quality. As used in GCTS, it is related to the RMS phase distortion at the aperture by the Strehl approximation

$$\frac{1}{(\mathrm{TDFLMT})^2} = \exp\left[-\left(\frac{2\pi\delta_{rms}}{\lambda}\right)^2\right] \tag{3.1}$$

$(\mathrm{TDFLMT})^2$, therefore, is equivalent to the ratio of the on-axis diffraction limited intensity to the on-axis intensity resulting from the near-field phase distortion, δ_{rms}.

$$\frac{1}{(\mathrm{TDFLMT})^2} = \frac{I}{I_0} \tag{3.2}$$

For a discussion of the limitation of 3.1, see [Ref. 19].

• WAVEBQ (*)

This term is the RMS phase distortion at the laser aperture, nondimensionalized by the wavelength.

$$\mathrm{WAVEBQ} = \frac{\delta_{rms}}{\lambda} \tag{3.3}$$

• SCALEQ (meters)   default = DIA/5

This term is the transverse phase correlation length at the aperture.

• THSEE (arcsec) default = f(RHOO)

This is a qualitative term used by astronomers to describe 'seeing conditions' in the visible range. If a point source is viewed from the earth, it may not appear as a point source but as a 'smear' or spot. The angular spread of this spot is the parameter THSEE. If RHOO is not specified as an input and THSEE is, the program will use THSEE to compute RHOO. Other than this case, THSEE is not used but will be computed as a function of RHOO and included as an output.

• HGRND (meters)

The height of the ground at the transmitter position above MSL.

• HTRANS (meters)

The height of the transmitter above.

• HSAT (meters)

The orbital altitude of the satellite above MSL (at zenith).

• THETMX (degrees)

THETMX is the angle measured from zenith below which the laser will not transmit for a zenith pass. For offset flight paths, it should be noted that the transmitter will point below this value. For an illustration of the engagement envelope, see figure 3.1

• IOFF (meters)

For a target that does not pass direct overhead, this input specifies the amount that the target ground track is offset from the ground track of the overhead case. It is the distance, as measured from the transmitter, to a perpendicular intersection on the ground track.

• RHO0 (meters) default = f(THSEE) or RHOTRB

This is the turbulence coherence length as defined by H. T. Yura. [Ref. 20]. (see turbulence section for more discussion and references)

• V0 (m/sec)

The atmospheric wind. The direction of the wind is parallel and opposite to the direction of target motion. Note, in the present program, V0 is a constant independent of altitude.

• AOBLOM (*) 0.0 to 1.0

This parameter allows the user to correct for thermal blooming as if by adaptive optics. The value entered may range from 0.0 to 1.0. If 0.0 is used, complete thermal blooming compensation will occur. Conversely, if 1.0 is entered, no compensation will be applied. The variance of the phase distortion is multiplied by this correction factor before the Strehl relation is used to compute the relative intensity reduction due to thermal blooming.

$$\frac{I}{I_0} = \exp(-\sigma^2 * \text{AOBLOM}) \tag{3.4}$$

• AVGSPT (*) 0.0 to 1.0

AVGSPT allows the user latitude in defining the far-field spot size to other than that indicated by GUTSAVG analysis. A value of 1.0 would result in the peak irradiance according to the program analysis. An entered value of .5, for example, would result in a peak irradiance 50% less than the program would otherwise indicate. AVGSPT, then, is an adjustment factor that allows the user to account for effects not addressed in the GUTSAVG propagation calculations.

• SIGJIT (radians)

SIGJIT is the $2\sigma_p$ variance for pointing and tracking jitter.

• ADAP (*) 0.0 to 1.0

This term is a correction factor for tilt due to turbulence. It represents the residual tilt after AO compensation. ADAP may be varied from 0.0 to 1.0. A value of 1.0 would result in no tilt due to turbulence being removed while a value of 0.0 would result in total tilt due to turbulence compensation. If full AO is selected the program will set ADAP equal to 0.0.

• NFLAGA (*) 0 or 1

NFLAGA is a selection indicator for full zonal adaptive optics. Enter a 0 if AO is not desired, enter a 1 if AO is desired. If AO is used, XJT,BWIDTH, and NA must be specified.

• NOISO (*) 0 or 1

NOISO is a selection indicator for isoplanatic calculations. Enter a 1 to inhibit isoplanatic calculations; enter a 0 if isoplanatic calculations are desired.

• XJT (Watts/sterad)

XJT is the target radiant intensity. It is one of the factors used to determine how noise affects the response of the AO system.

• BWIDTH (Hz)

BWIDTH is the bandwidth of the adaptive optics system.

• NA (*)

NA is the number of AO actuaters used to perform phase adjustment.

• ABSICZ (*)

This is the percent transmission at zenith at the sensing wavelength of the AO system. This term is used in the determination of relative noise at the AO sensor.

• N1 (*)

The number of iteration steps for the angle loop of the program from THETMX to 0.

• N2 (*)

The number of altitude intervals for absorption and scattering determination.

• N3 (*)

The number of altitude intervals for the turbulence calculations.

• N4 (*)

The number of iteration intervals for the MTF calculations.

• N5 (*)

The number of intervals for the slant path update of thermal blooming.

E. ENGAGEMENT GEOMETRY

The target engagement geometry is that of a earth-based transmitter and a target satellite at a given orbit. No attempt is made to define an engagement envelope based on threshold irradiance or fluence[1]. The input parameters defining the engagement window in GUTSAVG are THETMX, ICFF, and HSAT. The general geometry of this window is shown in Figure 3.1 . Only half of the total transit window is addressed in the program calculations; the results are the

---

[1] The GUTSFP (footprint) version of guts was written to do this. Except for this feature, the propagation calculations are identical to GUTSAVG.

same for either half. The program output reflects this half-window evaluation except for parameters such as total fluence and shot time which are simply double the computed values.

Figure 3.2 defines the earth center angle (ECANG). ECANG is a function of the user input THETMX. Most of the geometric calculations are referenced to earth center. Therefore, this angle is used for computing such positioning data as the angle interval at which the irradiance will be evaluated (see Figure 3.3).

Offset flight paths require a coordinate translation as shown in Figure 3.4 . Position and velocity relative to the transmitter are computed as in Figure 3.5 . It should be noted that if the flight path is offset, the zenith angle will exceed THETMX for part or all of the window. This is because the window is defined in the x-z plane only.

H_s - Zenith altitude of target

θ_m - Maximum zenith angle for engagement (zenith path)

L_o - Offset distance



Figure 3.1 General Engagement Geometry.



$$\theta_e = \cos^{-1} \frac{R}{R_s} \sin\theta_m + \theta_m - \frac{\pi}{2}$$

S - Target satellite

T - Laser transmitter

θ_e - Earth center angle

θ_m - Maximum zenith angle for engagement

R_s - Earth center-to-target distance

R - Earth center-to-transmitter distance

Figure 3.2 Earth Center Angle (ECANG).



Figure 3.3 Angle Intervals for Irradiance Evaluation.



Figure 3.4 Coordinate Translation due to Flight Path Cffset.



<u>Velocity components</u>

$$V_x = -V_s \cos(\theta_e)$$

$$V_y = V_s \sin(\theta_e) \cos(\gamma)$$

$$V_z = V_s \sin(\theta_e) \sin(\gamma)$$

<u>Position</u>

$$X = R_s \sin(\theta_e)$$

$$Y = Ly \cdot \cos(\gamma) + (Z_0 - R - Lz) \cdot \sin(\gamma)$$

$$Z = -Ly \cdot \sin(\gamma) + (Z_0 - R - Lz) \cdot \cos(\gamma)$$

where $Z_0 = R_s \cos(\theta_e)$

<u>Range from transmitter(T) to satellite(S)</u>

$$R_{ts} = Z + X + Y$$

(For Ly and Lz definition, see Figure 3.4)

Figure 3.5 Velocity and Position Relative to Transmitter.

C. MAIN PROGRAM FLOW DIAGRAM

The main program mostly consists of geometry calculations and decision flow points. The decision points allow branching to adaptive optics and isoplanatic subroutines. Most of the propagation calculations are done within the subroutines. Only two major iteration loops reside in the main program, the angle interval loop and the combined MTF integration loop. The following is a general flow diagram for the main program. Decision variables are user inputs or program defined parameters.



Figure 3.6 Main Program Flow Diagram.



Figure 3.7 Main Program Flow Diagram (cont).



Figure 3.8 Main Program Flow Diagram (cont).



Figure 3.9 Main Program Flow Diagram (cont).



Figure 3.10 Main Program Flow Diagram (cont).



Figure 3.11 Main Program Flow Diagram (cont).



Figure 3.12 Main Program Flow Diagram (cont).



Figure 3.13 Main Program Flow Diagram (cont).



Figure 3.14 Main Program Flow Diagram (cont).



Figure 3.15 Main Program Flow Diagram (cont).



Figure 3.16 Main Program Flow Diagram (cont).

D. SUBROUTINE DESCRIPTION

1. ABSORB and SCAT

As noted in the preceding chapter, absorption and scattering effects are treated indentically. The ABSORB and SCAT algorithms perform the integration

$$T_a = \exp - \int_{h_t}^{h_{atm}} \alpha(h)\,dh \qquad (3.5)$$

$$T_s = \exp - \int_{h_t}^{h_{atm}} \sigma(h)\,dh \qquad (3.6)$$

The result is the transmission due to the total absorption or total scattering. The correction for slant range is applied within the angle interval loop of the main program and is simply

$$T = T^{(\sec\theta)} \qquad (3.7)$$

is the zenith angle of the target with respect to the transmitter.

The extinction coefficients for absorption (α) and for scattering (σ) are provided to the subroutines by a call to routines ALFA and ALFS respectively.

TABLE I

ABSORB and SCAT Program Variable Definitions

Variable	Fortran name Sub	Main	Definition
T_a (ABSORB)	T	TABSC	Total molecular transmission
T_s (SCAT)	T	TSCATO	Total scattered transmission
h_{atm} (meters)	HATMO	HATMO	Height of atmosphere
h_t (meters)	HT	HTRANS	Height above MSL of transmitter
$\alpha(h)$ $(km)^{-1}$	ALP	-	Absorption coef. at given altitude
$\sigma(h)$ $(km)^{-1}$	ALS	-	Scattering coef at given altitude
-	N	N2	# of integration intervals

2. ALFS and ALFA

These two routines are also identical. They provide the extinction coefficients to ABSORB and SCAT for a specified altitude. At each altitude where a coefficient value is desired, a linear interpolation is performed between data points supplied by the user. Data statements precede each of these subprograms, and it is with these statements that the absorption and scattering data should be entered. Units for the coefficient and corresponding altitude should be km^{-1} and km respectively.

TABLE II

ALFS and ALFA Program Variables and Definitions

Variable	Fortran name Sub	Fortran name Main	Definition
$\sigma(h)$ $(km)^{-1}$	S	AIS	Scattering coef. at specified altitude
$\alpha(h)$ $(km)^{-1}$	A	AIP	Absorption coef. at specified altitude
h (meters)	H	-	specific altitude
—	ALT(NL)	-	Altitude data list
—	ATA(NL)	-	Absorption data list
—	ATS(NL)	-	Scattering data list
—	NL	-	Number of points in data list

3. UOCST

For a gaussian beam with constant phase, the initial amplitude distribution at the transmitter aperture is

$$U(r) = U_0 \exp\left[-(r/w)^2\right] \tag{3.8}$$

where U_0 is the amplitude and w is the spot size [Ref. 21]. The purpose of UOCST is to compute the constant U_0 for a given aperture power.

By the scalar wave approximation, the intensity distribution is [Ref. 22]

$$I(r) = |U(r)|^2 \tag{3.9}$$

To relate the field distribution to the power, the intensity distribution is integrated over the aperture.

$$P_t = \pi \int_{r_i}^{r_o} I(r)\,dr^2 \tag{3.10}$$

Substituting 3.8 and 3.9 into 3.10

$$P_t = \pi \int_{r_i}^{r_o} U_0 \exp\left[-(r/w)^2\right] \quad dr^2 \tag{3.11}$$

then rearranging terms, produces the expression for U_0.

$$U = \left[P_t \left\{ \pi \int_{r_i}^{r_o} \left(\exp\left[-(r/w)^2\right] \right)^2 dr^2 \right\}^{-1} \right]^{\frac{1}{2}} \tag{3.12}$$

The integration limits r_o and r_i are the radius of the transmitter and the obscuration, respectively.

UOCST performs the integration in 3.12 using the trapezoidal rule. A call is made to subroutine FIELD to evaluate $\exp[-(r/w)^2]$ which is simply $U(r)$ with $U_0 = 1$. For this reason, U_0 is defined as unity when FIELD is called by UOCST.

TABLE III

UOCST Program Variables and Definitions

Variable	Fortran name Sub	Main	Definition
U_0 $(W)^{\frac{1}{2}}m^{-1}$	U0	-	Normalization constant
P_t (Watts)	P	PTOTAL	Total aperture exit power
-	N	NI	# of integration increments
r_o (meters)	RO	-	Outer radius of transmitter
r_i (meters)	RI	-	Radius of obscuration
$U(r)$ $(W)^{\frac{1}{2}}m^{-1}$	UR	-	Field amplitude at radius r
w (meters)	BMRAD	-	Radius of spot at aperture

4. FIELD

FIELD calculates the field distribution for a axi-symmetric Gaussian beam with constant phase.

$$U(r) = U_0 \exp\left[-(r/w)^2\right] \qquad (3.13)$$

TABLE IV

FIELD Program Variable Definitions

Variable	Fortran name Sub	Main	Definition
$U(r)$ $(W)^{\frac{1}{2}}m^{-1}$	UR	-	Field amplitude at r
U_0 $(W)^{\frac{1}{2}}m^{-1}$	U0	-	Normalization constant
w (meters)	BMRAD	-	Radius of spot at aperture

5. FARFLD

In the Fraunhofer region, the amplitude distribution can be found by taking the Fourier transform of the aperture distribution [Ref. 23]. Using polar coordinates and noting axial symmetry, $U(\rho)$ in the far-field can be expressed as

$$U(\rho)=\frac{1}{\lambda z}\int_a^b\int_0^{2\pi}U(r)\exp\left[-\left(\frac{i2\pi}{\lambda z}\right)\cdot r\rho\cdot\cos\theta\right]rdrd\theta \tag{3.14}$$

Using integral relation for the zero order Bessel function, equation 3.14 can be simplified to [Ref. 24]

$$U(\rho) = \frac{2\pi}{\lambda z}\int_a^b U(r)\ J_0\left(\frac{2\pi\rho r}{\lambda z}\right)\ rdr \tag{3.15}$$

The intensity in the far-field is then given by $I(r)=|U(r)|^2$ or in terms of equation 3.15

$$I(\rho) = \left(\frac{2\pi}{\lambda z}\right)^2 \left[\int_a^b U(r) J_0\left(\frac{2\pi\rho r}{\lambda z}\right) rdr\right]^2 \qquad (3.16)$$

where b and a are the radius of the transmitter and the radius of the obscuration, respectively. [Ref. 25]

FARFLD evaluates 3.16 at a specified number of increments in the far-field and assigns these values to an array F(i). F(i) is normalized with the total aperture power so that the MTF produced would be unity at the origin. Note, however, that when the MTF is computed in this case, the MTF is normalized so as to produce an Irel (intensity relative) value when integrated.

$$M_a(\overline{\rho}) = \left(\frac{2\pi}{\lambda z}\right)^2 \frac{P_t}{I_0} \int_0^r I(\overline{\rho}) J_0\left(\frac{2\pi\overline{\rho}r}{\lambda z}\right) \overline{\rho} d\overline{\rho} \qquad (3.17)$$

I_0 is determined by evaluating equation 3.16 with r=0.0.

TABLE V

FARFLD Program Variables and Definitions

Variable	Fortran name Sub	Fortran name Main	Definition
$k\,(m)^{-1}$	CKR	-	$(2\pi/\lambda)$
ρ	R1	-	Radius in far-field
r	R0	-	Radius in aperture
I_0 (Watts)	PMAXC	PMAXC	Far-field on-axis intensity for a diffraction limited beam
$I(r)$ (W/m^2)	F(I)	TISC	Irradiance in far-field
$M_a(\overline{\rho})$	G(I)	IRRMTF	Aperture MTF
-	DX2	DX	Aperture MTF increments
P_t(Watts)	P	PTOTAL	Total power in the aperture

6. FCIREL

If the 'times diffraction limited number' (TDFLMT) is not specified, this routine computes the Irel value due to beam quality which is then used to compute TDFLMT in the main program. The calculation performed is

$$Irel = 2\pi \int M_a(\overline{\rho})\ M_b(\overline{\rho})\ \overline{\rho}d\overline{\rho} \tag{3.18}$$

where M_a is the aperture MTF and M_b is the MTF for the beam quality phase screen. M_a is defined in subroutine FARFID so that this integration produces an Irel value. M_b is the beam

quality MTF as computed by subroutine MTFBQ. IDFLMT is computed in the main program and is 1/ Irel .

TABLE VI

BQIREL Program Variables and Definitions

Variable	Fortran name Sub	Main	Definition
N	-	IDFLMT	Times diff. limited #
Irel	REL	TBQ	-
$M_a(\overline{\rho})$	A(I)	IRRMTF	Aperture MTF
$M_b(\overline{\rho})$	F(I)	-	MTF for phase screen
-	N4	N4	# of iterations for MTF calculations

7. DETWAV

If the RMS phase distortion parameter (WAVEBQ) is not specified, this routine computes it based on the approximation

$$Irel = \exp(-\sigma^2) \tag{3.19}$$

where $\sigma = \frac{2\pi\delta_{rms}}{\lambda}$ and δ_{rms} is the RMS value of the phase distortion at the aperture. Irel is the intensity degradation due to beam quality and is equal to $1/(N)^2$. N is the input parameter IDFLMT. DETWAV first evaluates σ^2 using equation 3.19 and then uses this value as a starting point

to compute a more accurate σ^2 by iteration using subroutine EQIREL. σ^2 is used to compute the beam quality MTF and the beam quality Irel as in equation 3.18 . σ^2 is adjusted, and the process repeated until the Irel found by equation 3.18 is equal to that determined by $1/(N)^2$.

TABLE VII

DETWAV Program Variables and Definitioms

Variable	Fortran Name Sub	Main	Definition
$\left[\frac{2\pi\delta_{rms}}{\lambda}\right]^2$	VAREQ	VAREQ	Constant
$\frac{\delta_{rms}}{\lambda}$	WAVEEQ	WAVEEQ	Phase distortion parameter
$1/N^2$	RELO	-	1/(IDFLMT)^2

8. <u>MTFEQ and BM</u>

These two routines calculate the beam quality MTF array. The MTF is [Ref. 26]

$$M_b(\overline{\rho}) = \exp\left(-k^2\left[\sigma^2 - C_\phi(\overline{\rho})\right]\right) \qquad (3.20)$$

where $C_\phi(\rho)$ is the autocorrelation function of the phase and is the phase variance. $C_\phi(\rho)$ is assumed to be Gaussian. Letting $C_\phi(\rho) = \sigma^2\exp\left[-(\rho/L)^2\right]$, where L is the phase correlation length, results in [Ref. 27]

$$M_b(\overline{\rho}) = \exp\left[-\left(\frac{2\pi\delta_{rms}}{\lambda}\right)^2 \left(1-\exp\left[-(\overline{\rho}/L)^2\right]\right)\right] \quad (3.21)$$

$\frac{\delta_{rms}}{\lambda}$ is the wavelength RMS phase distortion and is an input parameter (WAVEEQ). L, also a user input (SCALEQ), will default to 1/5 the diameter of the aperture if not otherwise specified.

TABLE VIII

MTFEQ and BM Program Variables and Definitions

Variable	Fortran name Sub	Main	Definition
$\left[\frac{2\pi\delta_{rms}}{\lambda}\right]^2$	VAREQ	VAREQ	Beam quality variance
$M_b(\overline{\rho})$	F(I)	BQMTF	Beam quality MTF
-	N4	N4	# of MTF integration increments
$k\ (m)^{-1}$	-	-	$(2\pi/\lambda)$

9. ISOTRB

ISOTRB calculates the zenith isoplanatic angle for use in the adaptive optics portion of the program. The angle is given by [Ref. 28]

$$\Theta_0 = .314 \left[\frac{2.91}{6.88} \sec\theta \int_{h_t}^{h_{atm}} C_n^2(h)\ h^{5/3} dh \right]^{-3/5} \qquad (3.22)$$

For the near zenith case, $\sec\theta = 1$. C_n^2 is the refractive index structure constant and is calculated by subroutine CN2H as function of altitude. See Fried [Ref. 29] for a discussion of the above angle.

TABLE IX

ISOTRB Program Variables and Definitions

Variables	Fortran Name Sub	Fortran Name Main	Definition
Θ_0 (rad)	ISOANG	ISCANO	Zenith isoplanatic angle
C_n^2 (m)$^{-2/3}$	CN2	-	Refractive index structure constant
-	N	N3	Integration intervals for turbulence
θ (deg)	-	OMEGA	Zenith angle

10. SCINT and SINILS

If full adaptive optics are used, amplitude scintillation effects will act to degrade the performance of the

conventional phase correcting adaptive optics system. This subroutine computes the log amplitude variance of the scintillations for zenith transmission. The approximation used is

$$\sigma_z^2 = .56k^{7/6}\int_{h_t}^{h_{atm}} h^{5/6} C_n^2(h)\,dh \tag{3.23}$$

For the off zenith case

$$\sigma_z^2 = \sigma_z^2 \sec(\theta) \tag{3.24}$$

where θ is the zenith angle [Ref. 30]. The relative irradiance loss due to scintillation is

$$\text{AMP LOSS} = \exp\left(-\sigma_z^2 \sec(\theta)\right) \tag{3.25}$$

The correction for the off zenith case is applied in subroutine SINTLS in the angle loop of the main program when full adaptive optics are specified. This loss factor has been shown to be limited to approximately .55, therefore, a default value is used in the main program in the case where equation 3.25 yields a value less than 0.5 [Ref. 31].

TABLE X

SCINTLS and SCINT Program Variables and Definitions

Variable	Fortran Name Sub	Main	Definition
$k\ (m)^{-1}$	CK	-	$2\pi/\lambda$
$C_n^2\ (m)^{-2/3}$	CN2H	-	Refractive index structure constant
σ_x^2	SIGX2	SIGX2	Log amplitude variation
Amp loss	TAMP	TAMP	Loss caused by scintillation

11. CN2H

CN2H computes the index of refraction structure constant as a function of altitude. C_n^2 is determined using Hufnagel's model with an added term to include the near surface effects. [Ref. 32] [Ref. 33]

$$C_n^2 = (5.94\times10^{-53})h^{10}\exp\left(\frac{-h}{1000}\right) + (2.7\times10^{-16})\exp\left(\frac{-h}{1500}\right) + (10^{-14})\exp\left(\frac{-h}{100}\right) \qquad (3.26)$$

Here, the units of h are meters.

12. RHOTRB

This subroutine computes Yura's [Ref. 34] lateral coherence length, ρ_0, in terms of Fried's [Ref. 35] coherence diameter, r_0.

$$\rho_0 = r_0/2.1 \tag{3.27}$$

Substituting Fried's definition for r_0

$$\rho_0 = \frac{1}{2.1}\left[\frac{2.91}{6.88}\, k^2 \int_{h_t}^{h_{atm}} C_n(h)\, dh\right]^{-3/5} \tag{3.28}$$

TABLE XI

RHOTRB Program Variables and Definitions

Variable	Fortran Name Sub	Main	Definition
$k\ (m)^{-1}$	CK	-	$2\pi/\lambda$
$C_n^2\ (m)^{-2/3}$	CN2	-	Refractive index structure constant
ρ_0 (meters)	RHO	RHO0	Coherence length
-	N	N3	# of integration intervals for turbulence

13. JIT and MTFJIT

JIT AND MTFJIT function algorithmically the same as EM and MTFEQ. Together, they compute the jitter MTF array. MTFJIT is called by JIT for each radial increment. The jitter MTF is given by

$$M_j(\overline{\rho}) = \exp\left(\frac{k^2\overline{\rho}^2(2\sigma_p)^2}{8}\right) \tag{3.29}$$

where $2\sigma_p$ is a user specified input. As with beam quality, this quantity is applied at the aperture.

TABLE XII

JIT and MTFJIT Program Variables and Definitions

Variable	Fortran Name Sub	Main	Definition
$k\ (m)^{-1}$	CK	-	$2\pi/\lambda$
$M_j(\overline{\rho})$	F	JITMTF	Jitter MTF

14. ERTBHS

This subroutine calculates that part of thermal blooming not dependent on the slant path of the beam. The equation used by GUTSAVG for the phase distortion due to thermal blooming is

$$\Delta\phi(x,y) = \left[\frac{2\pi}{\lambda}\ \frac{n-1}{p_0}\ \frac{\gamma-1}{\gamma}\int_{-\infty}^{x'} I(x',y)\,dx'\right]$$

$$\times\left[\int_{h_t}^{h_{atm}} \frac{\alpha(h)\exp\left(-\sec\theta\int_{h_t}^{h}\alpha(h)+\sigma(h)\ dh\right)}{V_0\cos\xi + \omega h}\,dh\right] \quad (3.30)$$

Note that the first term in this expression is invariant with respect to beam path while the second term contains such path dependent variables as wind, wind due to slew, and extinction coefficients. The first term is evaluated by this subroutine and the remainder evaluated later in the program inside the shoot angle iteration loop by subroutine AV.

Standard values used for n_0-1, p_0, and γ are 2.72×10^{4}, 1.01×10^{5} J/m^3, and 1.4, respectively. A phase screen, P(i,j), is constructed by iteration of the intensity integral. Note that program performs this integration over a half plane of the aperture defined by $-b<y<b$ and $0<x<b$ where b is the aperture diameter. The results are adjusted later in subroutine PHVAR for this method.

TABLE XIII

PRTPHS Program Variables and Definitions

Variable	Fortran Name Sub	Main	Definition
k $(m)^{-1}$	CK	-	$2\pi/\lambda$
n_0-1	const.	-	Refractive index term (2.72×10^{4})
γ	const.	-	Ratio of specific heats (1.4)
p_0	const.	-	Atmos. pressure (1.01×10^{5}) N/m^2
$\phi(x,y)$	PH(i,j)	PH(i,j)	Thermal blooming phase array

15. RESPHS and COEFFS

Once the phase screen has been constructed by subroutine PRTPHS, subroutine RESPHS removes the mean, tilt, and focus curvature. The result is the phase aberration due to thermal blooming alone. Zernike polynomials are utilized for expressing these phase distortions with subroutine COEFFS providing the required coefficients. These polynomials are

$$Z_0(x,y) = a_0 \qquad \text{(mean)} \tag{3.31}$$

$$Z_1(x,y) = a_1 x \qquad \text{(x tilt)} \tag{3.32}$$

$$Z_2(x,y) = a_2 y \qquad \text{(y tilt)} \tag{3.33}$$

$$Z_3(x,y) = a_3(x^2+y^2)+a_4 \qquad \text{(focus)} \tag{3.34}$$

The expansion coefficients are given below and are computed relative to a uniform aperture weighting function $W(x,y)$. $W(x,y) = 1$ inside the aperture and zero elsewhere. The integrals have been multiplied by 2 to compensate for the half plane integration of subroutine PHRPHS.

$$f_0 = 2a_0 \quad \phi(x,y)W(x,y)\,dxdy \tag{3.35}$$

$$f_1 = 2a_1 \quad \phi(x,y)W(x,y)\,xdxdy \tag{3.36}$$

$$f_2 = 2a_2 \quad \phi(x,y)W(x,y)\,ydxdy \tag{3.37}$$

$$f_3 = 2 \quad (a_3(x^2+y^2)+a_4) \quad (x,y)W(x,y)\,dxdy \tag{3.38}$$

The final phase correction is given by

$$\phi(x,y) = \phi(x,y) - f_1Z_1(x,y) - f_2Z_2(x,y) - f_3Z_3(x,y) - f_0Z_0(x,y) \tag{3.39}$$

For a discussion of least squares fitting of Zernike polynomials, see [Ref. 36].

16. PHVAR

The phase variance due to thermal blooming is computed by this subroutine using the residual phase screen provided by RESPHS. Normalized with respect to the aperture field, the variance is given by

$$\sigma^2 = \frac{U(x,y)\phi^2(x,y) + U(x,y)\phi(x,y)^2}{U(x,y)} \qquad (3.40)$$

TABLE XIV

PHVAR, RESPHS, and COEFS Program Variable Definitions

Variable	Fortran Name Sub	Fortran Name Main	Definition
$\phi(x,y)$	PH(i,j)	PH(i,j)	Phase array
	SIGSQ0	SIGSQ0	Phase variance
$a_0 - a_4$	A1- A4	-	Zernike coeffs.
$f_0 - f_3$	PHMEAN PHTILTX PHTILTY PHFOCUS	- - - -	The expansion coefficients relative to a uniform weighting function

17. AV

AV evaluates the path dependent part (second term) of the thermal blooming equation 3.30 . (see section PRIPHS) $\alpha(h)$ and $\sigma(h)$ are the absorption coefficient and scattering coefficient, respectively. V_0 is the user specified wind and ω is the slew rate. The denominator represents the total transverse wind component across the beam. θ is the zenith angle

and ξ is the angle of attack of V_0 with respect to the beam. V_0 has been assumed to be opposite in direction and parallel to the target to transmitter LCS slew motion. Note also that V_0 will be applied as a constant the entire length of the beam path. This is discussed in chapter one.

TABLE XV

AV Program Variables and Definitions

Variance	Fortran Name Sub	Main	Definition
$\alpha(h)+\sigma(h)$	ALP	-	Total extinction coefficient
$\alpha(h)\ (km)^{-1}$	ALS	-	Absorption coeff.
$\sec(\theta)$	SECCMG	SECCMG	secant of zenith angle
V_0 (m/sec)	VO	VO	Wind
	PHIICT	PHIDCT	Slew rate
h_{atm} (meters)	HATMC	HATMC	Height of the atmosphere
h_t (meters)	HT	HTRANS	Height of the transmitter

18. BLOOM

The purpose of BLOOM is to provide reasonable results for thermal blooming degradation when the Irel values are below approximately 0.3. In this region, the exponential Strehl relation predicts unacceptably severe results. Therefore, when the phase variance is greater than 1.2, BLOOM computes an Irel value based on GUTSMTF results. GUTSMTF is a full wave optics propagation code using FFTs.

Curve fit polynomials were developed using GUISMTF results for both a uniform and a truncated Gaussian aperture distribution. The resulting polynomials are

$$Irel = \frac{1}{-.08705 + 2.9148\sigma + .1723\sigma^2} \tag{3.41}$$

$$Irel = \frac{1}{1.2877 - 2.6491\sigma + 4.09603\sigma^2} \tag{3.42}$$

If the profile under consideration is a truncated Gaussian, i.e. the aperture diameter greater than the waist diameter of the beam, then the routine uses the truncated Gaussian polynomial. Otherwise, a combination of the two are used,

$$Irel_{tb} = \left[1-(d/b)^2\right] Irel_u + (d/b)^2 Irel_{tg} \tag{3.43}$$

where d is the aperture diameter and b is the waist diameter of the beam. [Ref. 37]

TABLE XVI

BLOOM Program Variables and Definitions

Variable	Fortran Name Sub	Fortran Name Main	Definition
σ^2	S	SIGSQ	Phase variance
$Irel_{tb}$	T	TBLOOM	Total blooming produced Irel
$Irel_u$	TRU	-	Curve fit Irel for uniform aperture dist.
$Irel_{tg}$	TRG	-	Curve fit Irel for Gaussian aperture dist.

19. MTFATM

MTFATM computes the atmospheric MTF and if specified, applies a tilt due to turbulence correction. The MTF is given by

$$M_t(\overline{\rho}) = \exp\left[-(\overline{\rho}/D)^{5/3}\left[1-d(\overline{\rho}/D)^{1/3}\right](D/\rho_0)^{5/3}\right] \qquad (3.44)$$

where D is the aperture diameter, ρ_0 is the coherence diameter and d is defined as 1-ADAP. ADAP is the fractional residual tilt due to turbulence and is a user specified parameter. If ADAP=0, M_t will represent the fully turbulence tilt corrected MTF. If ADAP=1, M_t will be the uncorrected MTF and may be written as

$$M_t(\overline{\rho}) = \exp\left[-(\overline{\rho}/\rho_0)^{5/3}\right] \qquad (3.45)$$

ADAP may be any value between 0 and 1.

TABLE XVII

MTFATM Program Variables and Definitions

Variable	Fortran Name Sub	Main	Definition
$M_t(\overline{\rho})$	F	F3	Atmospheric MTF
ρ_0(meters)	RHO	RHO	Coherence dia.
D (meters)	D	DIA	Aperture dia.

20. TRBREL

TRBREL computes the approximate Irel for a tilt corrected system. This value is used for comparison with the Irel produced by a prefect adaptive optics compensated system. The purpose of this comparison is to determine if noise will degrade the AO system to an extent as to make a full AO system undesirable. If this is the case, the program will apply tilt correction only to the beam.

21. FNDRHO

Subroutine FNDRHO calculates the coherence diameter that would result in the Irel value achieved by a perfect AO system. This is done by successive calls to subroutine TRBREI and iterating ρ_0. This new ρ_0 then becomes a factor in the AO compensation. Specifically it will be used by subroutine MTFATM to produce the atmospheric MTF of the AO corrected system.

TABLE XVIII			
IRREL and FNDRHC Program Variables and Definitions			

Variable	Fortran Name Sub	Main	Definition
$M_t(\bar{\rho})$	F2	-	Atmospheric MTF
$M_a(\bar{\rho})$	F1	IRRMTF	Aperture MTF
Irel	EXD	EXD	Irel of perfect AO system

22. TLTISO

The call to TLTISO is made when adaptive optics have not been user specified and isoplanatic calculations have not been inhibited. Also,if the signal to noise ratio at the AO sensor is such that the AO system will provide tilt correction only, TLTISO is called , again, provided isoplanatic calculations have not been inhibited.

The purpose of TLTISO is to include beam wander due to isoplanatism. The 2-sigma-p tilt is computed and combined with the jitter 2-sigma-p. This combined term is then used to compute the jitter MTF.

23. RELTOT

RELTOT simply averages the relative intensities due to a multiplicative and an RSS(root sum squared) approach to combining thermal blooming and the other propagation effects.

$$Irel = \frac{Irel_{rss} + Irel_m}{2} \tag{3.46}$$

$Irel_m$ is the result of the multiplicative approach

$$Irel_m = Irel_{tb} * Irel_o \tag{3.47}$$

where $Irel_{tb}$ is the Irel due to thermal blooming and $Irel_o$ is the Irel due to beam quality, jitter, turbulence , isoplanatism and adaptive optics effects. The RSS approach is given by

$$Irel_{rss} = \left[1 + \left(\frac{1}{Irel_o} - 1\right) + \left(\frac{1}{Irel_{tb}} - 1\right)\right]^{-1} \tag{3.48}$$

TABLE XIX

RELTOT Program Variables and Definitions

Variable	Fortran Name Sub	Main	Definition
$Irel_t$	T	TTOTAL	Total Irel
$Irel_{rss}$	TR	TRSS	Irel by RSS method
$Irel_m$	TM	TMULT	Irel by multiplicative method
	EXD	EXD	Irel of perfect AO system
$Irel_o$	-	TTRUE	Irel due to all other effects
$Irel_{tb}$	-	TBLOOM	Irel due to thermal blooming

24. ISOPLA

This routine calculates the MTF that characterizes the isoplanatic effect on the predictive or "look-ahead" adaptive optics system. The look-ahead angle is the major input parameter to this routine. The Fortran code was written by D.L. Fried [Ref. 38]. Fried developes the isoplanatic dependency of the AO system in terms of the effective antenna gain of the laser transmitter. The MTF that Fried formulates is given by

$$M_{iso}(\bar{\rho}) = \int^{\pi} 144.88 \cdot \lambda^{-2} \cdot \bar{\rho}^{-5/3} \cdot \sec(\theta) \cdot \mu(\nu \sec(\theta/\bar{\rho}), \phi)\, d\phi \qquad (3.49)$$

where

$$x = \nu \sec(\theta/\bar{\rho}) \qquad (3.50)$$

and

$$\mu(x,\phi) = \int C_n^2 \left\{ 1+(xh) \quad -\tfrac{1}{2}\left[1+2(xh)\cos\phi + (xh)^2\right]^{5/6} -\tfrac{1}{2}\left[1-2(xh)\cos + (xh)^2\right]^{5/6} \right\} dh \qquad (3.51)$$

θ is the zenith angle and ν is the target lead angle.

For detailed discussion of the theory and explicit development of the Fortran code, see [Ref. 39].

25. JO

JO computes the zero order Bessel function based on the input argument. This routine is called by FARFLD in the calculation of the far-field irradiance.

APPENDIX A

GUTSAVG INPUT FILE

```
INPUT DATA EIIE:

LASEE:        CO CW EDL      5P(9) TRANSITION         4.99210 MICRONS

CLIMATE:      MID-LATITUDE SUMMER, CLEAR DAY

CASE:         1

DIA       TELESCOPE DIAMETEF                 METERS        0.150000E+01
DIAOBS    CENTRAL OBSCURATION DIAMETER       METERS        0.150000E+00
BEAMSZ    GAUSSIAN WAIST THRU TELESCOPE      METERS        0.100000E+02
WAVE      CAVITY WAVELENGTH                  METERS        0.499210E-05
PTOTAL    APERTURE TOTAL POWER               WATTS         0.200000E+07
THSEE     TURBULENCE SEEING                  ARC-SEC       0.0
HGRND     HEIGHT OF GROUND ABOVE MSL         METERS        0.300000E+03
TDFLMT    TIMES DIFFRACTION LIMITED          -             0.120000E+01
WAVEEQ    RMS WAVES DISTORTION               -             0.0
SCALEQ    PHASE CORRELATION LENGTH           METERS        0.300000E+00
HTRANS    TRANSMITTER HEIGHT ABOVE MSL       METERS        0.300000E+03
HSAT      SATELLITE ALTITUDE                 METERS        0.100000E+07
THETMX    MAXIMUM ZENITH ANGLE               DEGREES       0.300000E+02
LOFF      FLIGHT PATH OFFSET                 METERS        0.0
RHOO      YURA'S TURB. COHERENCE DIA         METERS        0.0
VO        WIND VELOCITY                      M/SEC         0.600000E+01
SIGJIT    2-SIGMA-P JITTER                   RADIANS       0.500000E-05
ADAP      FRAC. RESID. TURB. TILT            -             0.100000E+01
AOBLCM    BLOOMING CORRECTION (0-1)          -             0.100000E+01
AVGSPT    SPOT AVERAGINF FACTOR (0-1)        -             0.100000E+01
NFLAGC    INCLUDE CLOUDS MODEL               -                        0
NFLAGA    USE FULL ZONAL A-C SYSTEM          -                        0
NOISO     INHIBIT ISOPLANATIC CALCS          -                        1
ABSLCZ    ZENITH TRANS FOR A-C SENSOR        -             0.750000E+00
XJT       TARGET RADIANT INTENSITY           W/STER        0.250000E+03
BWIDTH    A-C SYSTEM BANDWIDTH               HERTZ         0.500000E+03
NA        NUMBER OF A-C SYSTEM ACTUATORS                   0.102400E+04
N1        NUMBER OF ANGLE INTERVALS                                  30
N2        ABSORPTION INTEGRATION INTERVALS                          200
N3        TURBULENCE INTEGRATION INTERVALS                          100
N4        MTF INTEGRATION INTERVALS                                 200
N5        THERMAL BLOOMING INTEGRATION INTERVALS                    100
```

APPENDIX B

GUTSAVG OUTPUT FILE

```
LASER:        CO CW EDL      5P(9) TRANSITION          4.99210 MICRONS
CLIMATE:      MID-LATITUDE SUMMER, CLEAR DAY
CASE:         1
DIA      TELESCOPE DIAMETER               METERS          .150E+01
DIAOBS   CENTRAL OBSCURATION DIAMETER     METERS          .150E+00
BEAMSZ   GAUSSIAN WAIST THRU TELESCOPE    METERS          .100E+02
WAVE     CAVITY WAVELENGTH                METERS       .499210E-05
PTOTAL   APERTURE TOTAL POWER             WATTS           .200E+07
THSEE    TURBULENCE SEEING                ARC-SEC         .000E+00
HGRND    HEIGHT OF GROUND ABOVE MSL       METERS          .300E+03
TDPLMT   TIMES DIFFRACTION LIMITED          -             .120E+01
WAVERQ   RMS WAVES DISTORTION               -             .000E+00
SCALEQ   PHASE CORRELATION LENGTH         METERS          .300E+00
HTRANS   TRANSMITTER HEIGHT ABOVE MSL     METERS          .300E+03
HSAT     SATELLITE ALTITUDE               METERS          .100E+07
THETMX   MAXIMUM ZENITH ANGLE             DEGREES         .300E+02
LOFF     FLIGHT PATH OFFSET               METERS          .000E+00
RHO0     YURA'S TURB. COHERENCE DIA       METERS          .000E+00
VO       WIND VELOCITY                    M/SEC           .060E+02
SIGJIT   2-SIGMA-P JITTER                 RADIANS         .500E-05
ADAP     FRAC. RESID. TURB. TILT            -             .100E+01
AOBLCM   BLOOMING CORRECTION (0-1)          -             .100E+01
AVGSPT   SPOT AVERAGING FACTOR (0-1)        -             .100E+01
NFLAGA   USE FULL ZONAL A-O SYSTEM          -                    0
NOISC    INHIBIT ISOPLANATIC CALCS          -                    1
ABSLCZ   ZENITH TRANS FOR A-O SENSOR        -             .750E+00
XJT      TARGET RADIANT INTENSITY         W/STER          .250E+03
BWIDTH   A-O SYSTEM BANDWIDTH             HERTZ           .500E+03
NA       NUMBER OF A-O SYSTEM ACTUATORS                      1024.
N1       NUMBER OF ANGLE INTERVALS                              30
N2       ABSORPTION INTEGRATION INTERVALS                      200
N3       TURBULENCE INTEGRATION INTERVALS                      100
N4       MTF INTEGRATION INTERVALS                             200
N5       THERMAL BLOOMING INTEGRATION INTERVALS                100
```

PATH ANALYSIS RESULTS:

STEP NO.	RANGE (KM)	SLEW (MRAD/SEC)	OMEGA (DEG)	TIME (SEC)	ATMOS. TRANSMISSION SCAT	ABSORP	RHO (CM)
1.	999.738	7.1582	1.08	2.63	0.99802	0.53314	51.1
2.	1000.045	7.1541	2.16	5.27	0.99802	0.53302	51.0
3.	1000.659	7.1459	3.24	7.90	0.99802	0.53278	51.0
4.	1001.579	7.1337	4.31	10.53	0.99802	0.53242	51.0
5.	1002.805	7.1175	5.39	13.16	0.99801	0.53195	50.9
6.	1004.334	7.0973	6.46	15.80	0.99801	0.53135	50.9
7.	1006.167	7.0732	7.52	18.43	0.99800	0.53064	50.8
8.	1008.301	7.0453	8.59	21.06	0.99800	0.52982	50.8
9.	1010.735	7.0138	9.65	23.70	0.99799	0.52888	50.7
10.	1013.465	6.9786	10.70	26.33	0.99799	0.52782	50.6
11.	1016.490	6.9400	11.74	28.96	0.99798	0.52665	50.5
12.	1019.806	6.8981	12.79	31.59	0.99797	0.52537	50.4
13.	1023.413	6.8530	13.82	34.23	0.99796	0.52398	50.2
14.	1027.305	6.8048	14.85	36.86	0.99796	0.52248	50.1
15.	1031.481	6.7537	15.86	39.49	0.99795	0.52088	50.0
16.	1035.935	6.6999	16.87	42.13	0.99794	0.51917	49.8
17.	1040.666	6.6435	17.88	44.76	0.99792	0.51735	49.6
18.	1045.668	6.5847	18.87	47.39	0.99791	0.51544	49.5
19.	1050.939	6.5237	19.85	50.02	0.99790	0.51342	49.3
20.	1056.474	6.4606	20.83	52.66	0.99789	0.51130	49.1
21.	1062.269	6.3955	21.79	55.29	0.99787	0.50909	48.9
22.	1068.319	6.3288	22.75	57.92	0.99786	0.50679	48.7
23.	1074.621	6.2604	23.69	60.56	0.99785	0.50439	48.5
24.	1081.169	6.1907	24.63	63.19	0.99783	0.50191	48.3
25.	1087.959	6.1196	25.55	65.82	0.99781	0.49933	48.1
26.	1094.988	6.0475	26.46	68.45	0.99780	0.49668	47.9
27.	1102.250	5.9744	27.36	71.09	0.99778	0.49393	47.7
28.	1109.740	5.9006	28.25	73.72	0.99776	0.49111	47.4
29.	1117.455	5.8260	29.13	76.35	0.99774	0.48821	47.2
30.	1125.388	5.7510	30.00	78.99	0.99772	0.48524	47.0

TRANSMISSION ANALYSIS OUTPUT:

STEP	TRANSMISSION COEFFICIENTS DUE TO SPREADING	AMP LOSS WITH AO	THERMAL BLOOMING	RANGE SCALE	MAX IRRAD (KW/CM2)	FLUENCE (KJ/CM2)
1.	0.11826	1.00000	0.01522	0.9999	0.5779E-04	0.1522E-03
2.	0.11824	1.00000	0.01521	0.9993	0.5770E-04	0.3041E-03
3.	0.11821	1.00000	0.01518	0.9981	0.5753E-04	0.4555E-03
4.	0.11817	1.00000	0.01515	0.9963	0.5726E-04	0.6063E-03
5.	0.11810	1.00000	0.01511	0.9938	0.5692E-04	0.7562E-03
6.	0.11802	1.00000	0.01505	0.9908	0.5649E-04	0.9049E-03
7.	0.11793	1.00000	0.01499	0.9872	0.5597E-04	0.1052E-02
8.	0.11782	1.00000	0.01491	0.9830	0.5539E-04	0.1198E-02
9.	0.11770	1.00000	0.01483	0.9783	0.5472E-04	0.1342E-02
10.	0.11756	1.00000	0.01473	0.9730	0.5399E-04	0.1484E-02
11.	0.11740	1.00000	0.01463	0.9672	0.5320E-04	0.1624E-02
12.	0.11724	1.00000	0.01452	0.9610	0.5234E-04	0.1762E-02
13.	0.11705	1.00000	0.01440	0.9542	0.5142E-04	0.1898E-02
14.	0.11686	1.00000	0.01427	0.9470	0.5046E-04	0.2030E-02
15.	0.11664	1.00000	0.01414	0.9393	0.4945E-04	0.2161E-02
16.	0.11642	1.00000	0.01400	0.9313	0.4839E-04	0.2288E-02
17.	0.11618	1.00000	0.01385	0.9228	0.4730E-04	0.2413E-02
18.	0.11593	1.00000	0.01369	0.9140	0.4618E-04	0.2534E-02
19.	0.11566	1.00000	0.01354	0.9049	0.4504E-04	0.2653E-02
20.	0.11538	1.00000	0.01337	0.8954	0.4387E-04	0.2768E-02
21.	0.11509	1.00000	0.01320	0.8857	0.4268E-04	0.2881E-02
22.	0.11479	1.00000	0.01303	0.8757	0.4148E-04	0.2990E-02
23.	0.11448	1.00000	0.01286	0.8654	0.4028E-04	0.3096E-02
24.	0.11415	1.00000	0.01268	0.8550	0.3907E-04	0.3199E-02
25.	0.11381	1.00000	0.01250	0.8443	0.3786E-04	0.3298E-02
26.	0.11346	1.00000	0.01232	0.8335	0.3665E-04	0.3395E-02
27.	0.11310	1.00000	0.01213	0.8226	0.3545E-04	0.3488E-02
28.	0.11273	1.00000	0.01195	0.8115	0.3427E-04	0.3578E-02
29.	0.11235	1.00000	0.01176	0.8003	0.3309E-04	0.3666E-02
30.	0.11196	1.00000	0.01158	0.7891	0.3193E-04	0.3750E-02

```
CASE DATA AND CALCULATED FACTORS:

TRANSMITTER DIAMETER          =     150.00 CM
CAVITY WAVELENGTH             =   4.992100 UM
APERTURE TOTAL POWER          =     2.0000 MW
TIMES DIFFRACTION LIMIT       =       1.20
(WIDE ANGLE SCATTERING)
TRANSMITTER ALTITUDE          =     300.00 M
SATELLITE ALTITUDE            =    1000.00 KM
MAX ZENITH ANGLE              =      30.00 DEG
FLIGHT PATH OFFSET            =       0.0  KM
RHOO                          = 0.5105E+02 CM
WIND VELOCITY  .              =       6.00 M/SEC
HEIGHT OF GROUND              =     300.00 M
OPT SEEING AT 5500A           =   0.15E+01 ARC-SEC

BLOOMING ADAPTIVE OPTICS FACTOR  = 0.1000E+01
IRRADIANCE AREA AVERAGING FACTOR = 0.1000E+01

TELESCOPE DIMENSIONS:
OUTER DIAMETER               =     150.00 CM
INNER DIAMETER               =      15.00 CM
GAUSSIAN WAIST DIAMETER =    1000.00 CM

RMS WAVES DISTORTION        = 0.1031E+00
PHASE CORRELATION LENGTH = 0.3000E+02 CM

FOR THE FULL ZONAL A-C MODEL:
  ZENITH TRANS. AT A-C SENSOR   = 0.7500E+00
  TARGET RADIANT INTENSITY      = 0.2500E+03 W/STER
  ADAPTIVE OPTICS BANDWIDTH     = 0.5000E+03 HERTZ
  NUMBER OF ACTUATORS          =         1024.

THIS RUN -
  IS THE BASIC CODE WITH ONLY SOME MEASURE OF TILT CORRECTION
  AND WITHOUT AN ISOPLANATIC MODEL

NUMBER OF INTERVAL STEPS FOR:
  ANGULAR INTERVAL                    =         30
  ABSORPTION INTEGRATION              =        200
  RHO CALCULATION                     =        100
  MTF CALCULATION                     =        200
  THERMAL BLOOMING                    =        100

ZENITH LOG AMPLITUDE VARIANCE =  0.4905E-02
RELATIVE IRRADIANCE REDUCTION =  0.9951E+00

ZENITH LOOK-AHEAD ANGLE        = 0.5227E+02 URAD

ISOPLANATIC JITTER (2-SIGMA-P) = 0.2004E+07

2-SIGMA-P BEAM JITTER          =       5.00 URAD
TURBULENCE JITTER REJECTION    = 0.1000E+01
(RESIDUAL = INITAL * ADAP)


======== PROPAGATION RESULTS =======
INTEGRATED FLUX ON TARGET      =        0.007499 KJ/CM2
TOTAL ILLUMINATION TIME        =          157.97 SEC
```

APPENDIX C

GUTSAVG PROGRAM LISTING

```
C***************************************************************************
C                                                                          *
C  GUTSAVG         NAVAL POSTGRADUATE SCHOOL VERSION 1.2                   *
C                                                                          *
C  MODIFICATION 1.2                                                        *
C                                                                          *
C  LATEST CHANGE DATE 22 FEB 84                                            *
C                                                                          *
C  THIS VERSION OF GUTSAVG HAS BEEN MODIFIED FOR IBM 370/360               *
C  COMPATABILITY. VARIABLE NAME LENGTHS HAVE BEEN CHANGED AND               *
C  APPROAPRIATE FORTRAN CHANGES MADE. MACHINE GENERATED ERRORS MAY         *
C  STILL OCCUR DUE TO UNRESOLVED CDC/IBM DIFFERENCES                       *
C
C  THE CLOUD MODEL HAS BEEN REMOVED FROM THIS VERSION
C
C
C***************************************************************************
C
C============== MEMORY ALLOCATION AND VARIABLE  ASSIGNMENTS ===========C
C
      REAL BQMTF(300)
      REAL JITMTF(300)
      REAL A(100,14)
      REAL B(15)
      REAL PH(101,201)
      REAL TISC(300)
      REAL LOFF,MU
      REAL IRRMTF(300)
      REAL LY,IZ
      REAL NASQRT,NU,ISCANG,ISOANO,NA
C
      INTEGER TITLE1(80),TITLE2(80),TITLE3(80)
      INTEGER DESCR(40,60)
C
      COMMON /ATMO/ BATMO
      COMMON /BQ/ IDFLMT,VARBQ,WAVEBQ,SCALEQ
      COMMON /ABBFLD/ DIA,DIAOBS,BEAMSZ,U0
C
C============== CONSTANTS ASSIGNMENTS =================================C
C
      ML=201
      JJ=0
      TSTOLD=0.
      F4=1
      PI=2.*ARSIN(1.)
      MLH=ML/2+1
      BATMO=3.E4
      TAU=0.
      XMW=1.E+6
      XCM=1.E+2
      XKW=1.E-3
      XK2=1.E-7
      RTD=90./ARSIN(1.)
      REARTH=6.4E6
      MU=3.986E14
      THETSF=2.*PI/(24.*3600.)
      VSURF=REARTH*THETSF
C
      CALL ERRSET (208,256,-1,1,1)
C
C============== DATA INPUT SECTOR =====================================C
C
      READ (5,530)  (TITLE1(I),I=1,80)
      READ (5,530)  (TITLE2(I),I=1,80)
      READ (5,530)  (TITLE3(I),I=1,80)
C
      READ (5,510)  (DESCR(1,II),II=1,50), DIA
      READ (5,510)  (DESCR(2,II),II=1,50), DIAOBS
      READ (5,510)  (DESCR(3,II),II=1,50), BEAMSZ
      READ (5,510)  (DESCR(4,II),II=1,50), WAVE
      READ (5,510)  (DESCR(5,II),II=1,50), FTOTAL
      READ (5,510)  (DESCR(6,II),II=1,50), THSEE
      READ (5,510)  (DESCR(7,II),II=1,50), BGRND
C
C-----------------------------------------------------------------------
C      (EITHER IDFLMT OR WAVEBQ MUST BE DEFINED, BUT NOT BOTH)
```

```
C-----------------------------------------------------------------------
C
      READ (5,510) (DESCR(8,II),II=1,50), TDFLMT
      READ (5,510) (DESCR(9,II),II=1,50), WAVEBQ
      READ (5,510) (DESCR(10,II),II=1,50), SCALBQ
      READ (5,510) (DESCR(11,II),II=1,50), HTRANS
      READ (5,510) (DESCR(12,II),II=1,50), HSAT
      READ (5,510) (DESCR(13,II),II=1,50), THETMX
      READ (5,510) (DESCR(14,II),II=1,50), LOFF
      READ (5,510) (DESCR(15,II),II=1,50), RHOO
      READ (5,510) (DESCR(16,II),II=1,50), VO
      READ (5,510) (DESCR(17,II),II=1,50), SIGJIT
      READ (5,510) (DESCR(18,II),II=1,50), ADAP
      READ (5,510) (DESCR(19,II),II=1,50), AOBLOM
      READ (5,510) (DESCR(20,II),II=1,50), AVGSPT
      READ (5,520) (DESCR(21,II),II=1,50), NFLAGA
      READ (5,520) (DESCR(22,II),II=1,50), NOISO
C
C-----------------------------------------------------------------------
C     IF FULL AC CORRECTION IS NOT USED, THE following
C     PARAMETERS ARE NOT REALLY USED. ONLY BWIDTH
C     HAS AN EFFECT, it CAUSES the LOOK AHEAD ANGLE TO
C     BE LARGER BY TAU*PHIDOT.
C-----------------------------------------------------------------------
C
      READ (5,510) (DESCR(23,II),II=1,50), ABSLOZ
      READ (5,510) (DESCR(24,II),II=1,50), XJT
      READ (5,510) (DESCR(25,II),II=1,50), BWIDTH
      READ (5,510) (DESCR(26,II),II=1,50), NA
C
C-----------------------------------------------------------------------
C     ITERATION LOOP LIMITS:
C     N1 NUMBER OF SUBTHETA INTERVALS FROM 0 TO THETMX
C     N2 NUMBER OF INTEGRATION INTERVALS FOR ABSORPTION
C     N3 NUMBER OF INTEGRATION INTERVALS FOR TURBULENCE
C     N4 NUMBER OF INTEGRATION INTERVALS FOR MTF
C     N5 NUMBER OF SUBINTERVALS USED FOR SLANT PATH UPDATE FOR
C     THERMAL BLOOMING
C-----------------------------------------------------------------------
C
      READ (5,520) (DESCR(27,II),II=1,50), N1
      READ (5,520) (DESCR(28,II),II=1,50), N2
      READ (5,520) (DESCR(29,II),II=1,50), N3
      READ (5,520) (DESCR(30,II),II=1,50), N4
      READ (5,520) (DESCR(31,II),II=1,50), N5
C
C============== ECHO CHECK OUTPUT SECTOR ==============================C
C
      WRITE (6,190)
      WRITE (6,195) (TITLE1(I),I=1,80)
      WRITE (6,195) (TITLE2(I),I=1,80)
      WRITE (6,195) (TITLE3(I),I=1,80)
      WRITE (6,180) (DESCR(1,II),II=1,50), DIA
      WRITE (6,180) (DESCR(2,II),II=1,50), DIAOBS
      WRITE (6,180) (DESCR(3,II),II=1,50), BEAMSZ
      WRITE (6,180) (DESCR(4,II),II=1,50), WAVE
      WRITE (6,180) (DESCR(5,II),II=1,50), PTOTAL
      WRITE (6,180) (DESCR(6,II),II=1,50), THSEE
      WRITE (6,180) (DESCR(7,II),II=1,50), HGBND
      WRITE (6,180) (DESCR(8,II),II=1,50), TDFLMT
      WRITE (6,180) (DESCR(9,II),II=1,50), WAVEBQ
      WRITE (6,180) (DESCR(10,II),II=1,50), SCALBQ
      WRITE (6,180) (DESCR(11,II),II=1,50), HTRANS
      WRITE (6,180) (DESCR(12,II),II=1,50), HSAT
      WRITE (6,180) (DESCR(13,II),II=1,50), THETMX
      WRITE (6,180) (DESCR(14,II),II=1,50), LOFF
      WRITE (6,180) (DESCR(15,II),II=1,50), RHOO
      WRITE (6,180) (DESCR(16,II),II=1,50), VO
      WRITE (6,180) (DESCR(17,II),II=1,50), SIGJIT
      WRITE (6,180) (DESCR(18,II),II=1,50), ADAP
      WRITE (6,180) (DESCR(19,II),II=1,50), AOBLOM
      WRITE (6,180) (DESCR(20,II),II=1,50), AVGSPT
      WRITE (6,185) (DESCR(21,II),II=1,50), NFLAGA
      WRITE (6,185) (DESCR(22,II),II=1,50), NOISO
      WRITE (6,180) (DESCR(23,II),II=1,50), ABSLOZ
      WRITE (6,180) (DESCR(24,II),II=1,50), XJT
```

```
      WRITE  (6,180)  (DESCR(25,II),II=1,50), BWIDTH
      WRITE  (6,180)  (DESCR(26,II),II=1,50), NA
      WRITE  (6,185)  (DESCR(27,II),II=1,50), N1
      WRITE  (6,185)  (DESCR(28,II),II=1,50), N2
      WRITE  (6,185)  (DESCR(29,II),II=1,50), N3
      WRITE  (6,185)  (DESCR(30,II),II=1,50), N4
      WRITE  (6,185)  (DESCR(31,II),II=1,50), N5
C
C=============== DATA REALIGNMENT SECTOR ===============================C
C
      IF (SCALBQ.EQ.0.) SCALBQ=DIA/5.
      IF (WAVEBQ.NE.0.) VARBQ=(2.*PI*WAVEBQ)**2
      SGJITO=SIGJIT
      IF (NFLAGA.EQ.1) ADAP=0.
      IF (NOISC.EQ.1) ISOANO=1.E10
      NASQRT=SQRT(NA)
      LOGABS=-ALOG(ABSLC2)
      TAU=1./BWIDTH/PI
C
C=============== INITIAL CALCULATIONS SECTOR ===========================C
C
      IF (RHOO.EQ.0.AND.THSEE.NE.0.) RHOO=(WAVE/.55E-6)**1.2*(.054/THSEE
     1)
      THETMX=THETMX/RTD
      HSATD=HSAT-HTRANS
      HABVGD=HTRANS-HGRND
      IF (HABVGD.LT.0.) HABVGD=0.
C
      R=REARTH+HTRANS
      RS=REARTH+HSAT
      NFLGSN=0
C
C-----------------------------------------------------------------------
C     COMPUTE EARTH CENTER ANGLE OFF-SET
C-----------------------------------------------------------------------
C
      ANGOFF=LOFF/R
      A2=ANGOFF/2.
C
C-----------------------------------------------------------------------
C     COMPUTE COORDINATE TRANSLATIONS DUE TO OFF-SET
C-----------------------------------------------------------------------
C
      LY=+2.*R*SIN(A2)*COS(A2)
      LZ=2.*R*SIN(A2)**2
C
C-----------------------------------------------------------------------
C     COMPUTE EARTH CENTER ANGULAR RATE
C-----------------------------------------------------------------------
C
      THETDT=SQRT(MU/RS**3)
C
C-----------------------------------------------------------------------
C     COMPUTE ORBITAL SPEED
C-----------------------------------------------------------------------
C
      VSAT=THETDT*RS
C
C-----------------------------------------------------------------------
C     ADJUST INTENTANEOUS SLEWRATE FOR ROTATION OF EARTH,
C     assuming both are colinear.
C-----------------------------------------------------------------------
C
      THETDT=ABS(THETDT-THETSF)
C
C-----------------------------------------------------------------------
C     COMPUTE VELOCITY OF SATELLITE RELATIVE TO THE TRANSMITTER SITE
C-----------------------------------------------------------------------
C
      VS=THETDT*RS
C
C-----------------------------------------------------------------------
C     COMPUTE INITIAL LIMITS ON THE TIME AND ANGLE EARTH CENTER
C     .for an or line flight path
C-----------------------------------------------------------------------
C
```

```
      ECANG=ARCOS(R*SIN(THETMX)/RS)+THETMX-PI/2.
      TIMEX2=ECANG/THETDT
      TIMTOT=2.*TIMEX2
      DTIME=TIMEX2/N1
C
C-----------------------------------------------------------------------
C     IF SATELITE ALTITITUDE IS AN THE ORDER OF THE RADIUS OF
C     THE earth, gutsfp (footprint)  WORKS BETTER BY SETTING
C     the time step instead of the angle step
C-----------------------------------------------------------------------
C
      IF (HSAT.GT.REARTH/2.) DTIME=10.
C
C-----------------------------------------------------------------------
C     COMPUTE VACUUM IRRADIANCE AND APERTURE MTF.  NOTE THAT THE
C     POINT SPACING HERE MUST BE THE SAME AS USED IN THE MTF
C     INTEGRATION BELOW.   HENCE WE DEFINE DX NOW.
C-----------------------------------------------------------------------
C
      DX=DIA/N4
C
C-----------------------------------------------------------------------
C     THE CALL TO UOCST DETERMINES THE CONSTANT THAT MAKES THE EXIT
C     APERTURE POWER PTOTAL.
C-----------------------------------------------------------------------
C
      CALL UOCST (PTOTAL,M1)
      CALL PARFLD (DX,TISC,IRRMTF,M1,N4,HSATD,WAVE,PTOTAL,PMAXO)
C
C-----------------------------------------------------------------------
C     IF THE WAVEBQ IS NOT SPECIFIED AS INPUT, COMPUTE ON BASIS OF
C     TDFLMT.
C-----------------------------------------------------------------------
C
      IF (WAVEBQ.EQ.0.) CALL DETWAV (IRRMTF,DX,N4)
C
C-----------------------------------------------------------------------
C     IF TDFLMT WAS NOT SPECIFIED, COMPUTE IT .
C-----------------------------------------------------------------------
C
      IF (TDFLMT.NE.0.) GO TO 10
      CALL BQIBEL (IRRMTF,N4,DX,TBQ)
      TDFLMT=SQRT(1./TBQ)
10    CONTINUE
C
C-----------------------------------------------------------------------
C     DEFINE BEAM QUALITY MTF ARRAY.
C-----------------------------------------------------------------------
C
      CALL BM (BQMTF,DX,N4)
C
C-----------------------------------------------------------------------
C     DEFINE JITTER MTF ARRAY.
C-----------------------------------------------------------------------
C
      CALL JIT (JITMTF,DX,N4,SGJITC,WAVE)
C
C-----------------------------------------------------------------------
C     COMPUTE ZENITH ABSORPTION, SCATTERING, AND RHOO VALUES.
C-----------------------------------------------------------------------
C
      CALL ABSCRB (N2,HTRANS,TABSO)
      CALL SCAT (N2,HTRANS,TSCATO)
      IF (RHOO.EQ.0.) CALL RHOTRB (N3,HTRANS,HABVGD,WAVE,RHOO)
C
C-----------------------------------------------------------------------
C     DEFINE SEEING AT 5500A
C-----------------------------------------------------------------------
C
      THSEE=(WAVE/.55E-6)**1.2*(.054/RHOO)
C
      IF (NPLAGA.GE.1.AND.NOISO.EQ.0) CALL ISCTRB (N3,HTRANS,HABVGD,WAVE
     1,ISOANO)
C
C-----------------------------------------------------------------------
C     CALCULATE LOG AMPLITUDE SCINTILLATION FOR ZENITH ANGLE.
```

```
C-----------------------------------------------------------------------
C
      CALL SCINT (SIGX2,N3,HTRANS,HGRND,WAVE)
C
C-----------------------------------------------------------------------
C     COMPUTE THE THERMAL BLOOMING PHASE DISTORTION THAT does not depend
C     SLANT PATH CHARACTERISTICS
C-----------------------------------------------------------------------
C
      CALL PRTPHS (MI,MLH,WAVE,PH)
      CALL RESPHS (MI,MLH,PH)
      CALL PHVAR (MI,MLH,PTOTAL,PH,SIGSQO)
C
C-----------------------------------------------------------------------
C     INITIALIZE ACCUMULATED FLUENCE TO ZERO
C-----------------------------------------------------------------------
C
      FLUX=0.
C
C-----------------------------------------------------------------------
C     SET SNR FLAG TO OFF
C-----------------------------------------------------------------------
C
      NFLGSN=0
C
C
C*************** M A I N    P R O G R A M    L O O P *****************C
C
C-----------------------------------------------------------------------
C     LOOP ON IRRADIANCES AND ACCUMULATED FLUENCES FOR A FIXED LOFF
C-----------------------------------------------------------------------
C
      DO 120 I=1,N1
C
C-----------------------------------------------------------------------
C     COMPUTE TOTAL LENGTH OF ILLUMINATION TIME FROM (+,-)
C     OVER PASS ANGLE
C     THIS IS THE TOTAL TIME.  WE USE HALF OF THIS TO DETERMINE THE
C     FUNCTION EVALUATION ANGLE.
C-----------------------------------------------------------------------
C
      TIME=2.*((I-1)*DTIME+DTIME/2.)
C
C-----------------------------------------------------------------------
C     COMPUTE EARTH CENTER ANGLE AT ON LINE COORDINATES AND TIME/2.
C     THIS ANGLE IS TO THE MID-POINT OF THE INTEGRATION INTERVAL.
C     THE ANGLE ECANGF,COMPUTED LATER, IS TO THE UPPER LIMIT OF THE
C     integration limit.
C
C****** THE COMMENTED ECANG SHOULD BE USED WHEN IT IS DESIRED THAT
C       THE INTEGRATION SHOULD START AT THE LOW POINT AND INCREASE
C       TOWARDS THE ZENITH.  THE CURRENT CALCULATION STARTS AT
C       THE ZENITH AND GOES DOWN.
C-----------------------------------------------------------------------
C
C***  ECANG=(TIMTOT-TIME)/2.*THETDT
C
      ECANG=TIME/2.*THETDT
C
C-----------------------------------------------------------------------
C     COMPUTE TARGET COORDINATES
C-----------------------------------------------------------------------
C
      X0=RS*SIN(ECANG)
      Z0=RS*COS(ECANG)
      X=X0
      Y=LY*COS(ANGOFF)+(Z0-R+LZ)*SIN(ANGOFF)
      Z=-LY*SIN(ANGOFF)+(Z0-R+LZ)*COS(ANGOFF)
C
C-----------------------------------------------------------------------
C     COMPUTE ON LINE OF SIGHT ANGLE OF SAT.
C     THIS ANGLE IS NOT USED AT PRESENT .   IT IS THE ANGLE OF THE
C     SAT AS MEASURED FROM A POINT UNDER THE GROUND TRACK .
C-----------------------------------------------------------------------
C
      THETA=ATAN(RS*SIN(ECANG)/(RS*COS(ECANG)-R))
```

```
C
C-----------------------------------------------------------------------
C       CCMPUTE BANGE TC TABGET
C-----------------------------------------------------------------------
C
        BANGE=SQBT(X**2+Y**2+Z**2)
C
C-----------------------------------------------------------------------
C       INSTANTANEOUS SIEW BATE
C-----------------------------------------------------------------------
C
        VX=VS*COS(ECANG)
        VY=-VS*SIN(ECANG)*SIN(ANGOFF)
        VZ=-VS*SIN(ECANG)*CCS(ANGOFF)
        WX=Y*VZ-Z*VY
        WY=Z*VX-X*VZ
        WZ=X*VY-Y*VX
C
        PHIDOT=SQBT(WX**2+WY**2+WZ**2)/BANGE**2
C
C-----------------------------------------------------------------------
C       CCMPUTE ANGLE FBCM ZENITH
C
C       OMEGA EQUALS ANGLE DCWN FROM ZENITH
C       OMWIND EQUALS ANGLE CF WIND ATTACK TC LCS IF TARGET
C       MCTION AND WIND ARE COPLANAR.
C-----------------------------------------------------------------------
C
        OMEGA=ABCCS(Z/BANGE)
        OMWIND=ABSIN(X/BANGE)
C
        COSOMG=CCS(OMEGA)
        SECOMG=1./COSCMG
        COSWND=CCS(OMWIND)
C
C-----------------------------------------------------------------------
C       ADJUST FCB SLANT PATH, BLOOMING LOSS, ABSCBPTION LOSS, SCATTEBING
C       LCSS, AND TURBULENCE RHO
C
C-----------------------------------------------------------------------
C
C
        CALL AV (N5,VC,PHIDCT,HTBANS,CCSWND,cosomg,E)
        SIGSQ=SIGSQ0*E
C
C-----------------------------------------------------------------------
C       APPLY THEBMAL BLCCMING
C       ADAPTIVE OPTICS DEGREE OF COMPENSATION
C-----------------------------------------------------------------------
C
        SIGSQ=SIGSQ*ACBICE
C
        SIG=SQBT(SIGSQ)
        TBLOOM=EXP(-SIGSQ)
        IF (SIGSQ.GT.1.2) CALL BLOOM (DIA,BEAMSZ,SIGSQ,TBLOOM)
        TABS=TABS0**SECCMG
        TSCAT=TSCAT0**SECCMG
        BHC=BHO0*COSCMG**(.6)
C
C-----------------------------------------------------------------------
C COMPUTE LOOK AHEAD ANGLE ASSUMING EABTH ROTATION AND SATELLITE MOTION
C ABE IN THE SAME DIBECTION.
C-----------------------------------------------------------------------
C
        TWCT=RANGE*2./3.E8
        DBT=TWOT*(ABS(VSAT-VSURF))
        PBCJAN=ABCOS(X/BANGE)
        PBCJ=DBT*SIN(PBCJAN)
        NU=PROJ/BANGE+TAU*PHIDOT
        IF (I.EQ.1) ZENNU=NU
C
C-----------------------------------------------------------------------
C       IF executed, the following is a full ao simulation
C-----------------------------------------------------------------------
C
        IF (NFLAGA.EQ.C) GC TC 40
```

```
C
C-----------------------------------------------------------------------
C     MCDIFY RHC FCR EFFECT OF ADAPTIVE OPTICS
C-----------------------------------------------------------------------
C
      RHCLD=RHC
      RHOU=RHO
      RO=2.1*RHC
C
C-----------------------------------------------------------------------
C     DETERMINE APPRCXIMATE I-REL TC SEE IF AC SHOULD BE USED,
C     given PRESENt NOISE.
C-----------------------------------------------------------------------
C
      DCR=DIA/RHO
      CALL TRBREL (IRRMTF,DIA,N4,DX,EXDTST,RHC)
C
C-----------------------------------------------------------------------
C     COMPUTE RESIDUAL VARIANCE DUE TO PERFECT ADAPTIVE OPTICS,
C     INFINITE BANDWIDTH, AND FINITE NUMBER OF ACTUATORS.
C-----------------------------------------------------------------------
C
      D1=.320*(DIA/RO/NASQRT)**(1.6667)
      TES=LOGABS*SECCMG
      TSENSR=EXP(-TES)
C
C-----------------------------------------------------------------------
C     DETERMINE PHASE VARIANCE ASSOCIATED WITH SENSOR.
C-----------------------------------------------------------------------
C
      PHSERR=8.5E-6*BWIDTH*NA**2*(RANGE/5.E5*2.5/DIA)**4*(80./XJT*.5/TSE
     1NSR)**2
C
C-----------------------------------------------------------------------
C     INCREASE RESIDUAL PHASE VARIANCE AND CCMPUTE THE I-REL.
C-----------------------------------------------------------------------
      D1=D1+PHSERR
C
C-----------------------------------------------------------------------
C     COMPUTE I-REL CF AC TURBULENCE CORRECTED BEAM.
C-----------------------------------------------------------------------
C
      EXD=EXP(-D1)
C
C-----------------------------------------------------------------------
C     IF AO CORRECTED I-REL IS LESS THAN NC AC CORRECTION, ASSUME
C     ONLY TILT CORRECTICN IS USED.
C-----------------------------------------------------------------------
C
      IF (EXD.LT.EXDTST.OR.NFLGSN.EQ.1) GO TO 20
C
      CALL FNDRHO (EXD,RHO,DIA,RHOU,DX,N4,IRRMTF)
C
      GC TO 30
20    CONTINUE
C
C-----------------------------------------------------------------------
C     THIS SETS A FLAG TC PRINT THAT AO SYSTEM IS ONLY TILT
C-----------------------------------------------------------------------
C
      RHC=RHOLD
      NFLGSN=1
C
30    CONTINUE
C
C-----------------------------------------------------------------------
C     ESTABLISH TEST INCREMENTS TO SEE IF FULL ISOPLANATIC CALCULATION
C     NEEDS TO BE DCNE.
C-----------------------------------------------------------------------
C     COMPUTE THE ISCPLANATIC ANGLE.
C-----------------------------------------------------------------------
C
      ISOANG=CCSOMG**(2.6667)*ISOANO
      TSTNEW=NC/ISOANG
      TSTDIF=ABS(TSTNEW**1.666667-TSTOLD)
```

```
      ETSDIP=EXP(TSTDIF)
      IF (NISO.EQ.1) TSIOLD=TSTNEW**1.666667
C
C-----------------------------------------------------------------------
C     DETERMINE IF ISOPLANATIC MTF SHOULD BE RE-COMPUTED
C-----------------------------------------------------------------------
C
      NISO=0
      IF (ETSDIF.GT.1.1) NISO=1
      IF (I.EQ.1) NISO=1
      if (noisc.eq.1) niso=0
40    CONTINUE
C
C-----------------------------------------------------------------------
C     REDUCE PEAK IRRADIANCE BY SLANT DISTANCE
C-----------------------------------------------------------------------
C
      TMAXSC=(RSATD/RANGE)**2
C
C-----------------------------------------------------------------------
C    THIS ALLOWS ONE TO INCLUDE TILT ISOPLANATISM.  NOTE HOWEVER, THAT
C    IF THE FULL ADAPTIVE OPTICS ALGORITHM IS USED WITH THE ISOPLANATISM
C    CORRECTION, THEN THIS CALL SHOULD NOT BE USED-REPEAT-SHOULD NOT BE
C    USED.   ALSO NOTE THAT A VERTICAL TURBULENCE PROFILE IS NEEDED
C    WHEN EVER THIS ROUTINE IS USED.
C-----------------------------------------------------------------------
C
      IF (NFLGSN.EQ.1.AND.NOISO.EQ.0) GO TO 50
      IF (NOISC.EQ.1.OR.NFLAGA.EQ.1) GO TO 60
50    CONTINUE
      OMX=NU
      OMY=0.
      CALL TLTISO (DIA,OMX,OMY,RESTIT,SECOMG,HTRANS,HABVGD)
C
      SIGJIT=SQRT(SGJITC**2+RESTLT)
60    CONTINUE
C
C-----------------------------------------------------------------------
C     COMPUTE IRRADIANCE DECREASE DUE TO AMPLITUDE SCINTILLATION FOR THE
C     OFF ZENITH PASS.  NOTE THAT THIS AS LOSS WILL ONLY BE APPLIED IF
C     FULL ADAPTIVE OPTICS COMPENSATION IS ASSUMED.
C-----------------------------------------------------------------------
C
      CALL SINTLS (TAMP,SIGXZ,SECOMG)
C
C-----------------------------------------------------------------------
C     CALCULATE EFFECTS OF JITTER AND TURBULENCE
C-----------------------------------------------------------------------
C
      SUM=0.
      DX2=DX/2.
C
C-----------------------------------------------------------------------
C     IT IS IMPORTANT TO NOTE THAT ALL THE ARRAYS ARE DEFINED
C     TO BEGIN AT DX/2.
C-----------------------------------------------------------------------
C
      X=DX2
      DO 110 J=1,N4
      IF (X.GT.DIA) GO TO 100
      F1=IRRMTF(J)
      CALL MTFATM (X,DIA,RHO,ADAP,F2)
      F3=JITMTF(J)
      IF (NFLAGA.EQ.1.AND.NFLGSN.EQ.0) GO TO 70
      IF (NOISC.EQ.0) CALL MTFJIT (X,SIGJIT,WAVE,F3)
70    CONTINUE
      F4=1.
      IF (NFLAGA.EQ.0.OR.NOISO.EQ.1.OR.NFLGSN.EQ.1) GO TO 90
      F4=TISO(J)
      IF (NISO.EQ.1) CALL ISOPLA (JJ,NU,X,SECOMG,WAVE,F4,HTRANS,HABVGD,T
     1ISC,N4,J)
90    CONTINUE
      F5=BOMTF(J)
      SUM=SUM+F1*F2*F3*F4*F5*X
100   CONTINUE
      X=X+DX
```

```
110   CONTINUE
      TTURB=SUM*2.*PI*DX
C
C-----------------------------------------------------------------------
C     CALCULATE THE RESULTING INSTANTANEOUS INTENSITY
C-----------------------------------------------------------------------
C     CONVERT TO AN APPROCH WHICH AVERAGES THE RESULT OF AN RSS
C     TREATMENT OF THERMAL BLOOMING WITH A MULTIPLICATIVE TREATMENT
C-----------------------------------------------------------------------
C
      SSQT=1./TTURB-1.
      SSQB=1./TBLOOM-1.
      SSQ=SSQT+SSQB
      TMULT=TTURB*TBLOOM
      TRSS=1./(1.+SSQ)
      CALL RELTCT (TTOTAL,TRSS,TMULT)
      PMAX=PMAX0*TABS*TSCAT*TMAXSC*TTOTAL
C
C-----------------------------------------------------------------------
C     APPLY AVERAGING FACTOR
C     APPROPRIATE TO SPOT SIZE DESIRED
C-----------------------------------------------------------------------
C
      PMAX=PMAX*AVGSPT
C
C
C-----------------------------------------------------------------------
C     IF FULL AO IS USED, DECREASE IRRADIANCE FOR AMPLITUDE
C     SCINTILLATION EFFECTS
C-----------------------------------------------------------------------
C
      TAMPL=1.0
      IF (NFLAGA.EQ.1.AND.NFLGSN.EQ.0) TAMPL=TAMP
      IF (TAMPL.LT.0.5) TAMPL=0.5
      PMAX=PMAX*TAMPL
C
C-----------------------------------------------------------------------
C     ACCUMULATED FLUX
C-----------------------------------------------------------------------
C
      FLUX=FLUX+PMAX*DTIME
C
C-----------------------------------------------------------------------
C     COMPUTE INTEGRATED TIMES AND ACCUMULATED ANGLES. THE IRRADIANCE
C     FUNCTION HAS BEEN EVALUATED AT INTERVAL MID-POINTS.
C-----------------------------------------------------------------------
C
      ECANGF=(TIME+DTIME)/2.*THETDT
      XOF=RS*SIN(ECANGF)
      ZOF=RS*COS(ECANGF)
      XF=XOF
      YF=LY*COS(ANGOFF)+(ZOF-R+LZ)*SIN(ANGOFF)
      ZF=-LY*SIN(ANGOFF)+(ZOF-R+LZ)*COS(ANGOFF)
      RANGEF=SQRT(XF**2+YF**2+ZF**2)
C
      OMEGAF=ARCOS(ZF/RANGEF)
C
C-----------------------------------------------------------------------
C     TIME OF ILLUMINATION FROM ZENITH TO THETA. THIS IS ALSO
C     EVALUATED AT THE LOWER LIMIT AND NOT THE MID-POINT.
C     IF THE COMPUTATIONS ARE DONE FROM THE THETMX TO ZENITH INSTEAD
C     OF THE WAY THEY ARE, THE TIME DEFINITION NEEDS TO BE CHANGED.
C-----------------------------------------------------------------------
C
      TILLUM=TIME/2.+DTIME/2.
C
C============== LOOP RESULTS STORAGE SECTOR ============================C
C
      A(I,1)=I
      A(I,2)=RANGE*XKM
      A(I,3)=PRIDOT/XKM
      A(I,4)=OMEGAF*RTD
      A(I,5)=TILLUM
      A(I,6)=TSCAT
      A(I,7)=TABS
      A(I,8)=REC*XCM
```

```
      A(I,9)=TTURB
      A(I,10)=TAMPL
      A(I,11)=TELOCM
      A(I,12)=TMAXSC
      A(I,13)=PMAX*XK2
      A(I,14)=FLUX*XK2
120   CONTINUE
C
C============== FINAL RESULTS OUTPUT SECTOR ============================C
C
      B(1)=DIA*XCM
      B(2)=WAVE*XMW
      B(3)=PTOTAL/XMW
      B(4)=TDFIMT
      B(5)=HTRANS
      B(6)=HSAT*XKW
      B(7)=THETMX*RTD
      B(8)=LOFF*XKW
      B(9)=RHOO*XCM
      B(10)=V0
      B(11)=HGBND
      B(12)=THSEE
C
C
      WRITE (6,220)
      WRITE (6,240) ((A(I,J),J=1,8),I=1,N1)
      WRITE (6,230)
      WRITE (6,250) (A(I,1),(A(I,J),J=9,14),I=1,N1)
      WRITE (6,330) (B(LL),LL=1,12)
      WRITE (6,130) ACBICM,AVGSPT
C
      DIA=DIA*XCM
      DIAOBS=DIAOBS*XCM
      BEAMSZ=BEAMSZ*XCM
      WRITE (6,140) DIA,DIAOBS,BEAMSZ
C
      SCALBQ=SCALBQ*XCM
      WRITE (6,150) WAVEBQ,SCALBQ
      B(1)=ABSICZ
      B(2)=XJT
      B(3)=BWIDTH
      B(4)=NA
      WRITE (6,380) (B(LL),LL=1,4)
      WRITE (6,260)
      IF (NFLAGA.EQ.0.AND.NOISO.EQ.1) WRITE (6,310)
      IF (NFLAGA.EQ.1.AND.NOISO.EQ.0) WRITE (6,280)
      IF (NFLAGA.EQ.1.AND.NOISO.EQ.1) WRITE (6,290)
      IF (NFLAGA.EQ.0.AND.NOISO.EQ.0) WRITE (6,300)
      WRITE (6,340) N1,N2,N3,N4,N5
C
      ESIGXZ=EXP(-SIGXZ)
      WRITE (6,160) SIGXZ,ESIGXZ
C
      ZENNU=ZENNU*XMW
      WRITE (6,320) ZENNU
C
      RESTLT=SQRT(RESILT)*XMW
      WRITE (6,360) RESILT
C
      SGJITO=SGJITO*XMW
      WRITE (6,350) SGJITO,ADAP
C
      FLUX=FLUX*XK2*2.
      TILLUM=TILLUM*2.
      WRITE (6,370) FLUX,TILLUM
      IF (NFLGSN.EQ.1) WRITE (6,170)
      STOP
C
C=================== I/O FORMAT STATEMENTS =================================C
C
500   FORMAT (50X,F20.0)
510   FORMAT (50A1,E20.0)
520   FORMAT (50A1,I20)
530   FORMAT (80A1)
C
130   FORMAT(10X,'BLOCKING ADAPTIVE OPTICS FACTOR  = ',E10.4,/,
```

```
     1        1CX,'IRRADIANCE AREA AVERAGING FACTOR = ',E10.4,/)
140   FORMAT(10X,'TELESCOPE DIMENSIONS:',/,
     |        1CX,'OUTER DIAMETER          = ',F10.2,' CM',/,
     |        1CX,'INNER DIAMETER          = ',F10.2,' CM',/,
     |        10X,'GAUSSIAN WAIST DIAMETER = ',F10.2,' CM',/)
150   FORMAT(1CX,'RMS WAVES DISTORTICN        = ',E10.4,/,
     |        1CX,'PHASE CORRELTATION LENGTH = ',E10.4,' CM',/)
160   FORMAT (10X,'ZENITH LOG AMPLITUDE VARIANCE =',E12.4,/,10X,'RELA',
     1        'TIVE IRRADIANCE REDUCTICN =',E12.4,/)
170   FORMAT (10X,'NOTE=======THE ADAPTIVE OPTICS SYSTEM USED WILL ',
     1  'PROVIDE DEGRADED PERFORMANCE OVER THE TILT ONLY CASE',/)
180   FCRMAT (10X,50A1,E20.8)
185   FCRMAT (1CX,50A1,I20)
190   FCRMAT (1H1,9X,'INPUT DATA FILE:',//)
195   FCRMAT (1CX,80A1,/)
220   FORMAT (1H1,9X,'PATH ANALYSIS RESULTS:',//,
     |        6X,'STEP',10X,'RANGE',9X,'SLEW',6X,'OMEGA',7X,'TIME',
     |        5X,'ATMOS. TRANSMISSION',10X,'RHO',/,
     |        7X,'NO.',11X,'(KM)',5X,'(MRAD/SEC)',4X,'(DEG)',
     |        6X,'(SEC)',8X,'SCAT',6X,'ABSORP',9X,'(CM)',//)
230   FORMAT(1H1,9X,'TRANSMISSION ANALYSIS OUTPUT:',//,
     |     16X,'TRANSMISSICN COEFFICIENTS',13X,'RANGE',6X,'MAX IRRAD',
     |        11X,'FLUENCE',/,
     |        4X,'STEP',5X,'DUE TO',5X,'AMP LCSS',4X,
     |        'THERMAL ',4X,'SCALE',5X,'(KW/CM2)',5X,
     |        '(KJ/CM2)',/,10x,'SPREADING',6X,'WITH AO',5X,'BLOOMING',//)
240   FCRMAT(7X,F3.C,5X,F1C.3,5X,F8.4,5X,F6.2,5X,F6.2,5X,
     1        F7.5,5X,F7.5,5X,F8.1,/)
250   FORMAT(7X,F3.0,5X,F10.5,5X,F1C.5,5X,F10.5,5X,F10.4,5X,E10.4,
     |        5X,E10.4,/)
260   FCRMAT (10X,'THIS RUN -')
270   FCRMAT (12X,'INCLUDES THE STATISTICAL CLOUD MODEL')
280   FORMAT (12X,'INCLUDES THE FULL ZONAL AO MODEL WITH AN ',
     1        'ISOPLANATISM MODEL')
290   FORMAT (12X,'INCLUDES THE FULL ZONAL AO MODEL WITHOUT AN ',
     1        'ISOPLANATISM MODEL')
300   FORMAT (12X,'INCLUDES FULL TILT CORRECTION WITH TILT ',
     1        'ISOPLANATISM')
310   FORMAT (12X,'IS THE BASIC CODE WITH CNLY SOME MEASURE OF ',
     1        'TILT CORRECTION',/,12X,'AND WITHOUT AN ISOPLANATIC',
     2        ' MODEL',/)
320   FORMAT (10X,'ZENITH LOOK-AHEAD ANGLE        = ',E10.4,' URAD',/)
330   FORMAT(1H1,9X,'CASE DATA AND CALCULATED FACTORS:',//,
     |        1CX,'TRANSMITTER DIAMETER      = ',F10.2,' CM',/,
     |        10X,'CAVITY WAVELENGTH         = ',F10.6,' UM',/,
     |        1CX,'APERTURE TOTAL POWER      = ',F10.4,' MW',/,
     |        10X,'TIMES DIFFRACTION LIMIT   = ',F10.2,/,
     |        10X,'(WIDE ANGLE SCATTERING)',/,
     |        1CX,'TRANSMITTER ALTITUDE      = ',F10.2,' M',/,
     |        1CX,'SATELLITE ALTITUDE        = ',F10.2,' KM',/,
     |        1CX,'MAX ZENITH ANGLE          = ',F10.2,' DEG',/,
     |        10X,'FLIGHT PATH OFFSET        = ',F10.2,' KM',/,
     |        10X,'RHO0                      = ',E10.4,' CM',/,
     |        1CX,'WIND VELOCITY             = ',F10.2,' M/SEC',/,
     |        10X,'HEIGHT OF GROUND          = ',F10.2,' M',/,
     |        10X,'OPT SEEING AT 5500A       = ',E10.2,' ARC-SEC',/)
340   FORMAT(1CX,'NUMBER OF INTERVAL STEPS FOR:',/,
     |        12X,'ANGULAR INTERVAL             = ',I10,/,
     |        12X,'ABSORPTICN INTEGRATICN       = ',I10,/,
     |        12X,'RHO CALCULATICN              = ',I10,/,
     |        12X,'MTF CALCULATICN              = ',I10,/,
     |        12X,'THERMAL BLOOMING             = ',I10,/)
350   FCRMAT(1CX,'2-SIGMA-P BEAM JITTER         = ',F10.2,' URAD',/,
     |        10X,'TURBULENCE JITTER REJECTICN   = ',E10.4,/,
     |        10X,'(RESIDUAL = INITAL * ADAP)',/)
360   FCRMAT(10X,'ISCPLANATIC JITTER (2-SIGMA-P) = ',E10.4,/)
370   FCRMAT(///,10X,'======== PROPAGATION RESULTS ========',//,
     |        1CX,'INTEGRATED FLUX ON TARGET      = ',F15.6,' KJ/CM2',/,
     |        1CX,'TCTAL ILLUMINATION TIME        = ',F15.2,' SEC')
380   FORMAT(10X,'FOR THE FULL ZONAL A-O MODEL:',/,
     |        12X,'ZENITH TRANS. AT A-O SENSOR    = ',E10.4,/,
     |        12X,'TARGET RADIANT INTENSITY       = ',E10.4,' W/STER',/,
     |        12X,'ADAPTIVE OPTICS BANDWIDTH      = ',E10.4,' HERTZ',/,
     |        12X,'NUMBER OF ACTUATORS           = ',F10.0,/)
      END
```

```
      SUBROUTINE ALFA (A,Z)
C
C---- CALCULATE THE TOTAL MOLECULAR ABSORPTION
C
      DIMENSION ALT(20),ATA(20)
C
C******    THIS DATA FOR CO 5P9 FROM AFWL INFO, REPORTEDLY BASED ON AN
C******    UPDATE OF THE MCCLATCHY LINE DATA.  THE WAVELENGTH FOR THIS
C******    TRANSITION IS 4.99210 MICRONS.
C******    ATMOSPHERE IS MID-LATITUDE SUMMER, CLEAR DAY.
      DATA ALT/0.0,1.0,2.0,3.0,4.0,5.0,6.0,7.0,8.0,9.0,10.0,12.0,14.0,
     1        16.0,18.0,20.0,25.0,30.0,35.0,40.0/
      DATA ATA/0.356,0.269,0.148,7.28E-02,3.35E-02,1.51E-02,6.88E-03,
     1        3.40E-03,1.61E-03,1.79E-03,3.46E-04,6.50E-04,1.78E-05,
     2        1.06E-05,6.21E-06,3.61E-06,0.0,0.0,0.0,0.0/
      NL=19
      INDX=1
      A=0.
      IF ((Z*3.279).GE.1.E5) RETURN
      H=Z*1.E-3
C
C---- SEARCH FOR THE ALTITUDE INDEX
C
      DO 10 I=1,NL
      IF (H.LT.ALT(I)) GO TO 10
      INDX=I
10    CONTINUE
      R=(H-ALT(INDX))/(ALT(INDX+1)-ALT(INDX))
      A=R*(ATA(INDX+1)-ATA(INDX))+ATA(INDX)
      A=A/1000.
      RETURN
      END
```

```
      SUBROUTINE ALFS (S,Z)
C
C---- CALCULATE THE TOTAL SCATTERING
C
      DIMENSION ALT(20),ATS(20)
C
C******   THIS DATA FOR CO 5P9 FROM AFWL INFO, REPORTEDLY BASED ON AN
C******   UPDATE OF THE MCCLATCHY LINE DATA.  THE WAVELENGTH FOR THIS
C******   TRANSITION IS 4.99210 MICRONS.
C******   ATMOSPHERE IS MID-LATITUDE SUMMER, CLEAR DAY.
      DATA ALT/0.0,1.0,2.0,3.0,4.0,5.0,6.0,7.0,8.0,9.0,10.0,12.0,14.0,
     1          16.0,18.0,20.0,25.0,30.0,35.0,40.0/
      DATA ATS/1.41E-03,9.36E-04,1.09E-04,5.57E-05,4.54E-05,3.50E-05,
     1          2.60E-05,1.79E-05,1.14E-05,4.99E-05,3.64E-05,2.91E-05,
     2          2.62E-05,2.66E-05,2.41E-05,1.89E-05,7.00E-06,1.06E-05,
     3          3.28E-06,1.61E-06/
      NL=19
      S=0.
      IF ((Z*3.279).GE.1.E5) RETURN
      H=Z*1.E-3
      INDX=1
C
C---- SEARCH FOR THE ALTITUDE INDEX
C
      DO 10 I=1,NL
      IF (H.LT.ALT(I)) GO TO 10
      INDX=I
10    CONTINUE
      R=(H-ALT(INDX))/(ALT(INDX+1)-ALT(INDX))
      S=R*(ATS(INDX+1)-ATS(INDX))+ATS(INDX)
      S=S/1000.
      RETURN
      END
```

```
      SUBROUTINE ABSCBB (N,HT,T)
C
C---- CALCULATES ZENITH THE TOTAL INTEGRATED MOLECULAR TRANSMISSION
C
      COMMON /ATMO/ HATMO
      DELH=(HATMO-HT)/N
      HEIGHT=HT+DELH/2.
      ALPZ=0.
      DO 10 I=1,N
      CALL ALFA (ALP,HEIGHT)
      ALPZ=ALPZ+ALP
      HEIGHT=HEIGHT+DELH
10    CONTINUE
      ALPZ=ALPZ*DELH
      T=EXP(-ALPZ)
      RETURN
      END
```

```
      SUBROUTINE SCAT (N,HT,T)
C
C---- CALCULATES ZENITH THE TOTAL INTEGRATED SCATTERED TRANSMISSION
C
      COMMON /ATMO/ HATMO
      DELH=(HATMO-HT)/N
      HEIGHT=HT+DELH/2.
      ALPS=0.
      DO 10 I=1,N
      CALL ALFS (ALS,HEIGHT)
      ALPS=ALPS+ALS
      HEIGHT=HEIGHT+DELH
10    CONTINUE
      ALPS=ALPS*DELH
      T=EXP(-ALPS)
      RETURN
      END
```

```
      SUBROUTINE RHOTPB (N,HT,HG,W,RHC)
C
C---- COMPUTES YURAS ZENITH ATMOSPHERIC COHERENCE DIAMETER
C
      COMMON /ATMO/ HATMO
      TPI=4.*ARSIN(1.)
      CK=TPI/W
      CKSQ=CK*CK
      DELH=(HATMO-HT)/FLOAT(N)
      HEIGHT=HG+DELH/2.
      SUM=0.
      DO 10 I=1,N
      CALL CN2H (HEIGHT,CN2)
      SUM=SUM+CN2
      HEIGHT=HEIGHT+DELH
10    CONTINUE
      CNI=SUM*DELH
      DEN=2.91*CKSQ*CNI
      RHO=(6.88/DEN)**(.6)
      RHC=RHO/2.1
      RETURN
      END
```

```
      SUBROUTINE FARFLD (DX2,F,G,ML,N4,HSATD,WAVE,PTOTAL,PMAX0)
C
C---- COMPUTES THE FARFIELD IRRADIANCE OF THE APERTURE DISTRIBUTION
C---- AND THEN COMPUTES THE CORRESPONDING APERTURE MTF
C
      DIMENSION F(ML),G(ML)
      COMMON /ARBFLD/ DIA,DIAOBS,BEAMSZ,U0
      PI2=ARSIN(1.)
      PI=2.*PI2
      TWOPI=2.*PI
      CK=TWOPI/WAVE
      CKR=CK/HSATD
      DIASQ=DIA**2
      DOBSSQ=DIAOBS**2
      RFOCUS=1.2*HSATD*WAVE/SQRT(DIASQ-DOBSSQ)
      FACTOR=4.
      FACTOR=2.5
      FACTOR=5.
      RLIM=FACTOR*RFOCUS
      DX0=(DIA-DIAOBS)/2./ML
      DX1=RLIM/ML
      R1=DX1/2.
      DO 20 I=1,ML
      SUM=0.
      R0=DIAOBS/2.+DX0/2.
      DO 10 J=1,ML
      Z=CKR*R0*R1
      CALL J0 (Z,A)
      CALL FIELD (R0,UR)
      SUM=SUM+A*UR*R0
10    R0=R0+DX0
C        BY DIVIDING BY PTOTAL, THE MTF WILL BE UNITY AT THE ORIGIN.
      F(I)=(SUM*CKR*DX0)**2/PTOTAL
20    R1=R1+DX1
C
C---- COMPUTE PMAX0 ON AXIS
C
      SUM=0.
      R0=DIAOBS/2.+DX0/2.
      DO 30 I=1,ML
      CALL FIELD (R0,UR)
      SUM=SUM+UR*R0
30    R0=R0+DX0
      PMAX0=(SUM*CKR*DX0)**2
C
C---- CNORM- FIXES THE MTF SO THAT THE MTF INTEGRATION PRODUCES AN
C---- IDEL VALUE.
C
      CNORM=(WAVE*HSATD)**2*PMAX0/PTOTAL
C
C---- COMPUTE THE MTF
C
      R2=DX2/2.
      DO 50 I=1,N4
      SUM=0.
      R1=DX1/2.
      DO 40 J=1,ML
      Z=CKR*R1*R2
      CALL J0 (Z,A)
      SUM=SUM+A*F(J)*R1
40    R1=R1+DX1
      G(I)=SUM*TWOPI*DX1/CNORM
50    R2=R2+DX2
      RETURN
      END
```

```
      SUBROUTINE J0 (X,F)
C
C---- COMPUTES THE ZERO ORDER BESSEL FUNCTION.
C
C
C
C     DIMENSION A1(16),A2(11),A3(11),A4(15),A5(11),A6(11)
      REAL*8 A1(16),A2(11),A3(11),A4(15),A5(11),A6(11)
      DATA A1/-1.0D-15,4.1D-14,-1.944D-12,7.8487D-11,-2.679257D-9,7.6081
     1636D-8,-1.761946908D-6,3.2460328821D-5,-4.60626166206D-4,4.8191800
     269468D-3,-.034893769411409,.15806710233 2097,-.37009499387265,.2651
     378613203337,-.008723442352852,.31545594294978/
      DATA A2/1.0D-15,-5.0D-15,4.3D-14,-4.3D-13,5.168D-12,-7.8641D-11,1.
     1630646D-9,-5.1705945D-8,3.075184788D-6,-5.36522046813D-4,1.9989206
     29869504/
      DATA A3/-1.0D-15,4.0D-15,-3.3D-14,3.01D-13,-3.207D-12,4.2201D-11,-
     17.27192D-10,1.7972457D-8,-7.41449841D-7,6.8385199426D-5,-.03111170
     29210674/
      DATA A4/1.1D-14,-5.78D-13,2.5281D-11,-9.42421D-10,2.949707D-8,-7.6
     11758781D-7,1.588701924D-5,-.000260444389349,.003240270182684,-.029
     2175524806154,.177709117239728,-.66144393413 4543,1.28799409885768,-
     31.19180116054122,1.29671754121053/
      DATA A5/-1.0D-15,5.0D-15,-4.7D-14,4.7D-13,-5.705D-12,6.8169D-11,-1
     1.871891D-9,6.177634D-8,-3.9872843D-6,.000898989833086,2.0018060817
     22003/
      DATA A6/1.0D-15,-5.0D-15,3.6D-14,-3.26D-13,3.515D-12,-4.6864D-11,8
     1.22919D-10,-2.0559781D-8,9.13861526D-7,-9.62772354 92D-5,.09355574
     2139071/
C--- ZERO ORDER BESSEL FUNCTION
      N=0
C
      IF (N.EQ.1) GO TO 50
      IF (ABS(X).GT.8.0) GO TO 20
      Y=.0625*X*X-2
      B=0.0
      BP1=0.0
      DO 10 I=1,16
      BP2=BP1
      BP1=B
10    B=Y*BP1-BP2+A1(I)
      F=.5*(B-BP2)
      RETURN
20    Y=256/(X*X)-2
      AB=ABS(X)
      B=0.0
      BP1=0.0
      DO 30 I=1,11
      BP2=BP1
      BP1=B
30    B=Y*BP1-BP2+A2(I)
      P=.5*(B-BP2)
      B=0.0
      BP1=0.0
      DO 40 I=1,11
      BP2=BP1
      BP1=B
40    B=Y*BP1-BP2+A3(I)
      Q=4*(B-BP2)/AB
      Y=AB-.785398163397448
      F=.797884560802865*(P*COS(Y)-Q*SIN(Y))/SQRT(AB)
      RETURN
50    IF (ABS(X).GT.8.0) GO TO 70
      Y=.0625*X*X-2
      B=0.0
      BP1=0.0
      DO 60 I=1,15
      BP2=BP1
      BP1=B
60    B=Y*BP1-BP2+A4(I)
      F=.0625*(B-BP2)*X
      RETURN
70    Y=256/(X*X)-2
      AB=ABS(X)
      B=0.0
      BP1=0.0
      DO 80 I=1,11
      BP2=BP1
```

```
      BP1=B
80    B=Y*BP1-BP2+A5(I)
      P=.5*(B-BP2)
      B=0.0
      BP1=0.0
      DO 90 I=1,11
      BP2=BP1
      BP1=B
90    B=Y*BP1-BP2+A6(I)
      Q=4*(B-BP2)/AB
      B=SIGN(1.0,X)
      Y=AB-2.35619449019235
      F=.797884560802865*(P*COS(Y)-Q*SIN(Y))/SQRT(AB)
      F=B*F
      RETURN
      END
```

```
      SUBROUTINE FIELD (R,UR)
C
C---- COMPUTES EXIT APERTURE FIELD DISTRIBUTION.  NOTE IT MUST BE
C---- AXI-SYMETRIC.
C
      COMMON /APRPLD/ DIA,DIAOBS,BEAMSZ,U0
      UR=0.
      D=2.*R
      IF (D.GT.DIA.OR.D.LT.DIAOBS) RETURN
      BMRAD=BEAMSZ/2.
      UR=U0*EXP(-(R/BMRAD)**2)
      RETURN
      END
```

```
      SUBROUTINE UOCST (PT,N)
C
C---- COMPUTES NORMALIZATION CONSTANT GIVING PTOTAL ENERGY IN BEAM
C
      COMMON /ARBFLD/ DIA,DIAOBS,BEAMSZ,U0
      PI=2.*ARSIN(1.)
      RO=DIA/2.
      ROSQ=RO**2
      RI=DIAOBS/2.
      RISQ=RI**2
      DX=ROSQ/N
      CST=PI*DX
      X=DX/2.
      U0=1.
      SUM=0.
      DO 10 I=1,N
      ROOTX=SQRT(X)
      IF (ROOTX.GT.RO.OR.ROOTX.LT.RI) GO TO 10
      CALL FIELD (ROOTX,UR)
      SUM=SUM+UR**2
10    X=X+DX
      TEMP=SUM*CST
      U0=SQRT(PT/TEMP)
      RETURN
      END
```

```
      SUBROUTINE MTFATM (X,D,RHO,ADAP,F)
C
C---- COMPUTES ATMOSPHERIC MTF FUNCTION
C
      XD=X/D
      A1=1.-ADAP
      DRHO=D/RHO
      F=EXP(-XD**(1.6667)*(1.-A1*XD**(.3333))*DRHO**(1.6667))
      RETURN
      END
```

```
      SUBROUTINE MTFJIT (X,SIGJIT,WAVE,F)
C
C---- COMPUTES JITTER MTF FUNCTION
C
      TPI=4.*ARSIN(1.)
      CK=TPI/WAVE
      F=EXP(-(CK*X*SIGJIT)**2/8.)
      RETURN
      END
```

```
      SUBROUTINE MTFBQ (X,F)
C
C---- COMPUTES RANDOM PHASE MTF.  ASSUMES A GAUSSIAN CORRELATION
C---- FUNCTION.
C
      COMMON /BQ/ TDFLMT,VARBQ,WAVEBQ,SCALBQ
      TEMP=1.-EXP(-(X/SCALBQ)**2)
      F=EXP(-VARBQ*TEMP)
      RETURN
      END
```

```
      SUBROUTINE BQIREL (A,N4,DX,REL)
      DIMENSION A(N4)
      SUM=0.
      X=DX/2.
      DO 10 I=1,N4
      CALL MTFEQ (X,F)
      SUM=SUM+A(I)*F*X
      X=X+DX
10    CONTINUE
      REL=SUM*DX*6.2831852
      RETURN
      END
```

```
      SUBROUTINE DETWAV (A,DX,N4)
C
C---- IF THE RMS WAVES OF PHASE DISTORTION ARE NOT SPECIFIED,
C---- THEN THIS ROUTINE WILL DETERMINE THE APPROPRIATE WAVEBQ THAT
C---- PRODUCES THE SPECIFIED TDFLMT.
C
      COMMON /BQ/ TDFLMT,VARBQ,WAVEBQ,SCALEQ
      DIMENSION A(N4)
      REL0=1./TDFLMT**2
      VARBQ=-ALOG(REL0)
      DVBQ=VARBQ/10.
      TEST=.005
      NSIGN0=1.
10    CONTINUE
      CALL BQIREL (A,N4,DX,REL)
      DREL=REL-REL0
      IF (ABS(DREL)/REL0.LT.TEST) GO TO 40
      IF (DREL.LT.0.) GO TO 20
      NSIGN1=1
      GO TO 30
20    NSIGN1=-1
30    CONTINUE
      IF (NSIGN1.NE.NSIGN0) DVBQ=DVBQ/2.
      VARBQ=VARBQ+DVBQ*NSIGN1
      NSIGN0=NSIGN1
      GO TO 10
40    CONTINUE
      TWOPI=6.2831852
      WAVEBQ=SQRT(VARBQ)/TWOPI
      RETURN
      END
```

```
      SUBROUTINE JIT (A,DX,N4,SIGJIT,WAVE)
C
C---- COMPUTES ARRAY FOR JITTER MTF.
C
      DIMENSION A(N4)
      X=DX/2.
      DO 10 I=1,N4
      CALL MTFJIT (X,SIGJIT,WAVE,F)
      A(I)=F
10    X=X+DX
      RETURN
      END
```

```
      SUBROUTINE BM  (A,DX,N4)
C
C-----COMPUTES ARRAY FOR BEAM QUALITY MTF.
C
      DIMENSION A(N4)
      X=DX/2.
      DO 10 I=1,N4
      CALL MTFEQ (X,F)
      A(I)=F
10    X=X+DX
      RETURN
      END
```

```
      SUBROUTINE CN2H (HEIGHT,CN2)
C
C     CACULATE ATMOSPHERIC VERTICAL TURBULENCE
C
C---- HUFNAGELS LATEST MODEL-GOOD ONLY ABOVE 3 KILOMETERS
C
      CN2=2.2*(1.E-5*10.**(-.3)*HEIGHT)**10.*EXP(-HEIGHT/1000.)
      CN2=CN2+1.E-16*EXP(-HEIGHT/1500.)
      CN2=CN2*2.7
C
C---- THIS MODIFICATION IS USED to include turbulence at lower alts
C
      CN2=CN2+1.E-14*EXP(-HEIGHT/100.)
      RETURN
      END
```

```
      SUBROUTINE AV (N,V0,PHIDCT,HT,COSWND,cosomg,E)
C
C--- COMPUTES THAT PART OF THERMAL BLOOMING THAT CHANGES WITH SLANT PATH
C
      COMMON /ATMO/ HATMO
      COSSQ=COSWND
      DELH=(HATMO-HT)/N
      RG=DELH/2.
      HEIGHT=HT+DELH/2.
      VOCOS=V0*COSSQ
      SUM=0.
      SUMAS=0.
      DO 10 I=1,N
      CALL ALFA (ALA,HEIGHT)
      CALL ALFS (ALS,HEIGHT)
      SUMAS=SUMAS+ALS+ALA
      ALOSS=EXP(-SUMAS*DELH/COSOMG)
      SUM=SUM+ALOSS*ALA/(VOCOS+RG*PHIDCT)
      RG=RG+DELH
      HEIGHT=HEIGHT+DELH
10    CONTINUE
      SUM=SUM*DELH
      E=SUM**2
      RETURN
      END
```

```
      SUBROUTINE PRTPHS (ML,MLH,WAVE,PH)
C
C----- COMPUTES THAT PART OF THERMAL BLOOMING PHASE THAT DOES NOT DEPEND
C----- ON SLANT RANGE
C
      COMMON /ARBFLD/ DIA,DIAOBS,BEAMSZ,U0
      DIMENSION PH(MLH,ML)
      MLM=ML-1
      MLHM=MLH-1
      DIASQ=DIA**2
      RADSQ=DIASQ/4.
      PI4=ARSIN(1.)/2.
      CK=8.*PI4/WAVE
      SCALE=CK*(2.72E-4*.4)/(1.01E5*1.4)
      RCSQ=(DIA/2.)**2
      RISQ=(DIAOBS/2.)**2
      DELN=DIA/MLM
      XI=DELN/2.
      YI=-DIA/2.+DELN/2.
      X=XI
      DO 20 I=1,MLHM
      Y=YI
      SUM=0.
      XSQ=X*X
      DO 10 J=1,MLM
      RSQ=Y*Y+XSQ
      R=SQRT(RSQ)
      FACTOR=0.
      IF (RSQ.LT.RCSQ.AND.RSQ.GT.RISQ) CALL FIELD (R,FACTOR)
      FACTOR=FACTOR**2
      SUM=SUM+FACTOR
      PH(I,J)=SUM*SCALE*DELN
      Y=Y+DELN
10    CONTINUE
      X=X+DELN
20    CONTINUE
      RETURN
      END
```

```
      SUBROUTINE RESPHS (ML,MLH,PH)
C
C---- CALCULATES THE RESIDUAL PHASE AFTER THE MEAN,TILT, AND FOCUS
C---- HAVE BEEN REMOVED.
C
      DIMENSION PH(MLH,ML)
      COMMON /ABBFLD/ DIA,DIAOBS,BEAMSZ,U0
      MLHM=MLH-1
      MLM=ML-1
      DELN=DIA/MLM
      XI=DELN/2.
      YI=-DIA/2.+DELN/2.
      ROSQ=(DIA/2.)**2
      RISQ=(DIAOBS/2.)**2
C
C        COMPUTE NORMALIZATION CONSTANTS
C
      CALL COEFS (A0,A1,A2,A3,A4,MLM,MLHM,DELN)
C
C---- COMPUTE EXPANSION COEFFICIENTS
C
      SUM1=0.
      SUM2=0.
      SUM3=0.
      SUM4=0.
      X=XI
      DO 20 I=1,MLHM
      XSQ=X**2
      Y=YI
      DO 10 J=1,MLM
      YSQ=Y**2
      RSQ=XSQ+YSQ
      IF (RSQ.GT.ROSQ.OR.RSQ.LT.RISQ) GO TO 10
      CALL FIELD (SQRT(RSQ),UR)
C
C---- DETERMINE EXPANSION COEFFICIENTS RELATIVE TO A UNIFORM
C---- WEIGHTING FUNCTION.
C
      FT=0.
      IF (ABS(UR).GT.1.E-2) FT=1.
      FACTOR=PH(I,J)*FT
      SUM1=SUM1+FACTOR*X
      SUM2=SUM2+FACTOR*Y
      SUM3=SUM3+FACTOR*RSQ
      SUM4=SUM4+FACTOR
10    Y=Y+DELN
20    X=X+DELN
C------- ADJUST FOR HALF PLANE INTEGRATION
      SUM1=0.
      SUM2=SUM2*2.
      SUM3=SUM3*2.
      SUM4=SUM4*2.
C
      DELNSQ=DELN**2
      PHMEAN=A0*SUM4*DELNSQ
      PHTLTX=A1*SUM1*DELNSQ
      PHTLTY=A2*SUM2*DELNSQ
      PHFOC=(A3*SUM3+A4*SUM4)*DELNSQ
C
C
C---- SUBTRACT THE MEAN,TILT,AND FOCUS CURVATURES.
C
      X=XI
      DO 40 I=1,MLHM
      XSQ=X**2
      Y=YI
      DO 30 J=1,MLM
      YSQ=Y**2
      RSQ=XSQ+YSQ
      IF (RSQ.GT.ROSQ.OR.RSQ.LT.RISQ) GO TO 30
      PH(I,J)=PH(I,J)-PHTLTX*A1*X-PHTLTY*A2*Y-PHFOC*(A3*RSQ+A4)-PHMEAN*A
     10
30    Y=Y+DELN
40    X=X+DELN
      RETURN
      END
```

```
      SUBROUTINE COEFS (A0,A1,A2,A3,A4,MLM,MLBM,DELN)
C
C---- COMPUTES TILT AND FOCUS NORMALIZTION CONSTANTS
C
      COMMON /ARBFLL/ DIA,DIAOBS,BEAMSZ,UO
      ROSQ=(DIA/2.)**2
      RISQ=(DIAOBS/2.)**2
      DELNSQ=DELN**2
      YI=-DIA/2.+DELN/2.
      XI=DELN/2.
      X=XI
      SUM1=0.
      SUM2=0.
      SUM3=0.
      SUM4=0.
      DO 20 I=1,MLBM
      XSQ=X**2
      Y=YI
      DO 10 J=1,MLM
      YSQ=Y**2
      RSQ=XSQ+YSQ
      RSQSQ=RSQ**2
      IF (RSQ.GT.ROSQ.OR.RSQ.LT.RISQ) GO TO 10
      CALL FIELD (SQRT(RSQ),UR)
C
C-----DETERMINE NORMALIZATION COEFFICIENTS RELATIVE TO A UNIFORM
C-----WEIGHTING FUNCTION.
C
      FT=0.
      IF (ABS(UR).GT.1.E-2) FT=1.
      FACTOR=FT
      SUM1=SUM1+FACTOR
      SUM2=SUM2+FACTOR*XSQ
      SUM3=SUM3+FACTOR*YSQ
      SUM4=SUM4+FACTOR*RSQSQ
10    Y=Y+DELN
20    X=X+DELN
C-------- ADJUST FOR HALF PLANE INTEGRATION
      SUM1=SUM1*2.
      SUM2=SUM2*2.
      SUM3=SUM3*2.
      SUM4=SUM4*2.
C
      A0=SQRT(1./(SUM1*DELNSQ))
      A1=SQRT(1./(SUM2*DELNSQ))
      A2=SQRT(1./(SUM3*DELNSQ))
      B=-SUM1/(SUM2+SUM3)
      A3=SQRT(B*B/((B*B*SUM4-SUM1)*DELNSQ))
      A4=A3/B
C
      RETURN
      END
```

```
      SUBROUTINE PHVAR (ML,MLH,ETOTAL,PH,SIGSQO)
C
C-----COMPUTES THE THERMAL BLOOMING PHASE VARIANCE
C
C-----VARIANCE IS COMPUTED LIKE THE STREHL RATIO ACCORDING TO THE
C---- FIELD AS A WEIGHTING FUNCTION.
C
      COMMON /ARBFLD/ DIA,DIAOBS,BEAMSZ,U0
      DIMENSION PH(MLH,ML)
      RCSQ=(DIA/2.)**2
      RISQ=(DIAOBS/2.)**2
      MLM=ML-1
      MLHM=MLH-1
      DELN=DIA/MLM
      XI=DELN/2.
      YI=-DIA/2.+XI
      X=XI
      SUM1=0.
      SUM2=0.
      SUM3=0.
      DO 30 I=1,MLHM
      Y=YI
      XSQ=X*X
      DO 20 J=1,MLM
      RSQ=XSQ+Y*Y
      IF (RSQ.GT.RCSQ.OR.RSQ.LT.RISQ) GO TO 10
      CALL FIELD (SQRT(RSQ),UR)
      SUM1=SUM1+UR
      SUM2=SUM2+UR*PH(I,J)**2
      SUM3=SUM3+UR*PH(I,J)
10    CONTINUE
      Y=Y+DELN
20    CONTINUE
      X=X+DELN
30    CONTINUE
C-------- ADJUST FOR HALF PLANE INTEGRATION
      SUM1=SUM1+2.*DELN**2
      SUM2=SUM2+2.*DELN**2
      SUM3=SUM3+2.*DELN**2
C
C        NORMALIZE WITH RESPECT TO INTEGRAL OF THE FIELD.
C
      SIGSQO=SUM2/SUM1-(SUM3/SUM1)**2
C
      RETURN
      END
```

```
      SUBROUTINE ISOTRB (N,HT,HG,W,ISOANG)
C
C---- COMPUTE ZENITH ISOPLANATIC ANGLE BASED UPON D.L. FRIEDS
C-----DEFINITION
C
      COMMON /ATMO/ HATMO
      REAL ISOANG
      TPI=4.*ARSIN(1.)
      CK=TPI/W
      CKSQ=CK*CK
      DELH=(HATMO-HT)/N
      HEIGHT=HG+DELH/2.
      DHT=DELH/2.
      SUM=0.
      DO 10 I=1,N
      CALL CN2H (HEIGHT,CN2)
      SUM=SUM+CN2*DHT**1.66666667
      HEIGHT=HEIGHT+DELH
      DHT=DHT+DELH
10    CONTINUE
      CNI=SUM*DELH
      DEN=2.91*CKSQ*CNI
      ISOANG=(6.88/DEN)**.6*.314
      RETURN
      END
```

```
      SUBROUTINE ISOPLA (JJ,XNU,R,SECOMG,WAVE,XINT,HT,HG,TISO,N4,II)
C
C-----THIS SUBROUTINE COMPUTES THE ISOPLANATIC MTF FOR A FULL AO
C-----COMPENSATED SYSTEM DEVELOPED BY DL FRIED
C
      DIMENSION H(23),C(19),C2(19),C4(19)
      DIMENSION TISO(N4)
      DIMENSION S(19),XMU(20),CN2(23)
      COMMON /ATMO/ HATMO
      IF (JJ.GE.1) GO TO 30
      NH=20
      N=18
      DELH=(HATMO-HT)/NH
      HEIGHT=HG+DELH/2.
      DO 10 K=1,NH
      CALL CN2H (HEIGHT,CNSQ)
      CN2(K)=CNSQ
      H(K)=HEIGHT
10    HEIGHT=HEIGHT+DELH
      PI=3.1415926
      A13=1./3.
      A56=5./6.
      A572=5./72.
      A143=14./3.
      A9127=91./27.
      A73=7./3.
      A53=5./3.
      A12=1./2.
      DPHI=PI/2./N
      PHI=DPHI/2.
      DO 20 J=1,N
      C(J)=COS(PHI)
      PHI=PHI+DPHI
      C2(J)=C(J)*C(J)
20    C4(J)=C2(J)*C2(J)
30    CONTINUE
      JJ=JJ+1
      XA=XNU*SECOMG/R
      DO 40 J=1,N
40    S(J)=0.
      DO 110 K=1,NH
      X=H(K)*XA
      XX=CN2(K)
      IF (X.LT.0.1) GO TO 60
      IF (X.GT.10.) GO TO 80
      X2=X*X
      DO 50 J=1,N
      F=1.+X**A53-A12*(1.+2.*X*C(J)+X2)**A56-A12*(1.-2.*X*C(J)+X2)**A56
50    S(J)=S(J)+F*XX
      GO TO 100
60    X53=X**A53
      X2=X*X
      X4=X2*X2
      DO 70 J=1,N
      F=X53-A56*X2*(1.-A13*C2(J))+A572*X4*(1.-A143*C2(J)+A9127*C4(J))
70    S(J)=S(J)+F*XX
      GO TO 100
80    X13=X**(-A13)
      X73=X13/(X*X)
      DO 90 J=1,N
      F=1.-A56*X13*(1.-A13*C2(J))+A572*X73*(1.-A143*C2(J)+A9127*C4(J))
90    S(J)=S(J)+F*XX
100   CONTINUE
110   CONTINUE
      XMU(1)=1./XA
      DO 120 J=1,N
120   XMU(J+1)=114.88*DELH*S(J)
C
C       NOW INTEGRATE OVER PHI
C
      CST=R**A53*SECOMG/WAVE**2
      SUM=0.
      DO 130 I=1,N
130   SUM=SUM+EXP(-XMU(I+1)*CST)
C
C
```

```
C
      XINT=SUM*DPHI*2./PI
      TISO(II)=XINT
      RETURN
      END
```

```
      SUBROUTINE FNDBBC (EXD,RHO,DIA,RHOU,DX,N4,IRRMTF)
C
C---- THIS SUBROUTINE DETERMINES WHAT VALUE OF RHO WOULD PRODUCE THE AC
C---- CORRECTED STREHL AS IF THERE WERE NO COMPENSATION AT ALL
C
      REAL IRRMTF(N4)
C
      R=RHOU
      DR=RHOU/2.
      NSIGNO=-1
      NSIGN=-1
10    CONTINUE
      CALL TRBREL (IRRMTF,DIA,N4,DX,SR,R)
      IF (ABS(SR-EXD)/EXD.LT..1) GO TO 40
      DIF=SR-EXD
      IF (DIF.LT.0.) GO TO 20
      NSIGN=1
      GO TO 30
20    NSIGN=-1
30    CONTINUE
      IF (DIF.GE.0.) DR=DR/2
      NSIGNO=NSIGN
      R=R-DR*NSIGN
      GO TO 10
40    CONTINUE
      RHO=R
      RETURN
      END
```

```
      SUBROUTINE TRPREL (IRRMTF,DIA,N4,DX,TREL,RHO)
C
C---- THIS SUBROUTINE COMPUTES THE RELATIVE INTENSITY DUE TO A TOTAL
C-----TILT CORRECTED SYSTEM FOR TURBULENCE ONLY.
C
      REAL IRRMTF(N4)
      PI=2.*ARSIN(1.)
      SUM=0.
      DX2=DX/2.
      X=DX2
      DO 10 I=1,N4
      F1=IRRMTF(I)
      CALL MTFATM (X,DIA,RHO,0.,F2)
      SUM=SUM+F1*F2*X
      X=X+DX
10    CONTINUE
      TREL=SUM*2.*PI*DX
      RETURN
      END
```

```
      SUBROUTINE TLTISC (D,OMX,OMY,RESTLT,SECOMG,HTRANS,HABVGD)
C
C-----THIS SUBROUTINE COMPUTES THE RESIDUAL TILT DUE TO ISOPLANATISM
C
      COMMON /ATMO/ HATMO
      N=100
      E56=5./6.
      E53=5./3.
      DS=(HATMO-HTRANS)/N
      H=HABVGD+DS/2
      SUM=0.
C
      DO 10 I=1,N
C
      CALL CN2H (H,CN2)
C
      Z=SECOMG*H
C
      ARG1=((D+Z*OMX)**2+(Z*OMY)**2)**E56
      ARG2=((D-Z*OMX)**2+(Z*OMY)**2)**E56
      ARG3=(Z**2*(OMX**2+OMY**2))**E56
      ARG4=D**E53
      ARG5=((Z*OMX)**2+(D-Z*OMY)**2)**E56
      ARG6=((Z*OMX)**2+(D+Z*OMY)**2)**E56
C
      SUM=SUM+(4.*ARG4+4.*ARG3-ARG2-ARG5-ARG1-ARG6)*CN2
      H=H+DS
 10   CONTINUE
C
C---- THIS IS THE RESULTANT 2-SIGMA-P TILT DUE TO ISOPLANATISM.
C
      RESTLT=SUM*DS*SECOMG*2.91/D**2*2.
C
      RETURN
      END
```

```
      SUBROUTINE RELTOT (T,TR,TM)
C
C----- WE HAVE FOUND THE DETAILED MTF CODE TO GIVE RESULTS
C------ WHICH LIE BETWEEN AN RSS MODEL FOR BLOOMING AND A
C------ MULTIPLICATIVE APPROACH.  THIS SUBROUTINE IS AN ATTEMPT
C------ AT BETTER MATCHING THE RESULTS OF THE MTF CODE BY
C------ AVERAGING THE RSS AND THE MULTIPLICATIVE RESULTS.
C
C
      T=(TR+TM)/2.
      RETURN
      END
```

```
      SUBROUTINE BLOCM (D,B,S,T)
C
C-----THESE BLOOMING TREI MODELS ARE CURVE FITTED TO GUTSMTF
C-----RUNS FOR SIGSQ'S GREATER THAN ABOUT 1.2. THE APERTURE
C-----DISTRIBUTIONS USED HAD OBSCURATIONS OF .1 X THE OUTER
C-----DIAMETER.  IF BETTER IS REQUIRED, RECOMMEND BASELINING
C-----TO THE GUTSMTF CODE AGAIN.

      SQRTS=SQRT(S)
      TBG=-.08705+SQRTS*2.91485+.1723*S
      TBG=1./TBG
      TBU=1.2877-SQRTS*2.6491+4.09603*S
      TBU=1./TBU
      T=(1.-(D/B)**2)*TBU+(D/B)**2*TBG
      IF (D.GT.B) T=TBG
      RETURN
      END
```

```
      SUBROUTINE SCINT (SIGXZ,N,HTRANS,HGRND,WAVE)
C
C---- THIS ROUTINE COMPUTES THE VARIANCE OF THE LOG AMPLITUDE
C---- FOR A ZENITH ANGLE.  THE RESULTS WILL ONLY BE USED
C---- IN THE EVENT THAT FULL AO IS UTILIZED IN THE RUN.
C
      COMMON /ATMO/ HATMO
      CK=6.28/WAVE
      HTOTAL=HATMO-HTRANS
      DH=HTOTAL/N
      H=HTRANS+DH/2.
      C56=5./6.
      SUM=0.
      DO 10 I=1,N
      H56=H**C56
      CALL CN2E (H,CN2)
      SUM=SUM+CN2*H56
      H=H+DH
10    CONTINUE
      CK76=CK**(7./6.)*DH*0.56
      SIGXZ=SUM*CK76
      RETURN
      END
```

```
      SUBROUTINE SINTIS (TAMP,SIGXZ,SECOMG)
C
C---- COMPUTE THE LOG AMPLITUDE SCINTILLATION VARIANCE
C---- FOR OFF-ZENITH CONDITIONS AND THE RELATIVE IRRADIANCE
C---- REDUCTION WHEN FULL AO IS USED.
C
      TAMP=EXP(-SIGXZ*SECOMG**(11./6.))
      RETURN
      END
```

LIST OF REFERENCES

1. Air Force Weapons Laboratory TR-78-53-VCL-1, *Interactive Engagement Simulation Program* by D. W. Barret nad A. J. Cantor, v. 1, January 1979.

2. Lutomirski, R. F. and Yura, H. T., "Propagation of a Finite Optical Beam in a Inhomogeneous Medium", *Applied Optics*, v. 10, pp 1652- 1658, July 1971.

3. Air Force Weapons Laboratory TR-78-53-VCL-1, *Interactive Engagement Simulation Program* by D. W. Barret nad A. J. Cantor, v. 1,pp 95-98, January 1979.

4. Walsh, J. L. and Ulrich, P. B. "Thermal Blooming in the Atmosphere", *Laser Beam Propagation in the Atmosphere*, J. W. Strohbehn, editor, pp 250 -251, Springer-Verlag, 1978.

5. Hogge, C. B. "Propagation of High Energy Laser Beams in the Atmosphere", *High Energy Lasers and Their Applications*, Physics of Quantum Electronics series, v. 1 ,pp 216-222, 1975.

6. Holmes, D. A. and Avizonis, P. V. "Approximate Optical System Model", *Applied Optics*, v. 15, pp 1080-1081, April 1976.

7. Personal communication with Capt. A. Boye, AFWL, Albuquerque NM.

8. Personal communication with Capt. A. Boye, AFWL, Albequerque NM.

9. Carey, E. F. and Fuhs, A. E. "Transonic Thermal Blooming due to an Intense Laser Beam", *Journal of Aircraft*, v. 13, pp 974-980, December, 1976.

10. Fuhs, A. E., "Propagation of Laser Beams which are Rapidly Slewed", *Proceedings of Electro-Optical Systems Design / International Laser Conference, 1975*.

11. O'Neill, E. L., *Introduction to Statistical Optics*, pp 99-101, Addison-Wesley, 1963.

12. Hogge, C. B., Butts, R. R., and Burkaloff, M "Characteristics of Phase-Aberrated Nondiffraction Limited Laser Beams", *Applied Optics*, v. 13,pp 1065-1067, May, 1974.

13. Hufnagel, R. E. "Variations of Atmospheric Turbulence", _Topical Meeting on Optical Propagation Through Turbulence_, Optical Society of America, 1974.

14. Fried, D. L., "Limiting Resolution Looking Down Through the Atmosphere", _Journal of the Optical Society of America_, v. 56, pp 1380-1384, October 1966.

15. Yura, H. T., "Atmospheric Turbulence Induced Laser Spread", _Applied Optics_, v. 10, p 2771, December 1971.

16. Yura, H. T., "An Elementary Derivation of Phase Fluctuations of an Optical Wave in the Atmosphere", _Proceedings SPIE_ v. 75, pp 9 - 15 ,1976.

17. Negro, J. E., "Pointing Variance and Beam Degradation Calculations", _Laser Digest_, AFWL-TR-74-100, pp 59-67, May 1974

18. Fried, D. L., "Anisoplanatism in Adaptive Optics", _Agard Conference Proceedings_, no. 300, p 46-1, 1980.

19. Holmes, D. A., and Avizonis, P. V., "Approximate Optical System Model", _Applied Optics_, v. 15, pp 1080-1081, April 1976.

20. Yura,H. T., "Atmospheric Turbulence Induced Laser Spread", _Applied Optics_, v. 10, p 2771, December 1971.

21. Hogge, C. B., Butts, R. R., and Burkaloff,M, "Characteristics of Phase-Aberrated Nondiffraction Limited Laser Beams", _Applied Optics_, v. 13,pp 1065-1067,May 1974.

22. Born, M., and Wolf,E., _Principles of Optics_, 4th ed.,p 387, Pergamon Press,1970.

23. Goodman, J. W., _Introduction to Fourier Optics_, pp 57-65,McGraw-Hill,1968.

24. Goodman, J. W., _Introduction to Fourier Optics_, pp 12-13, McGraw-Hill, 1968.

25. Air Force Weapons Laboratory TR-70-102, _Integrated Focal Plane Irradiance Patterns for Gaussian Beams Focused Through Circular Apertures_, by D. A. Holmes, p 3, October 1970.

26. O'Neill,E. L., _Introduction to Statistical Optics_, pp 99-101, Addison-Wesley,1963.

27. Hogge, C. B., Butts, R. R., and Burkaloff, M, "Characteristics of Phase-Aberrated Nondiffraction Limited Laser Beams", _Applied Optics_, v. 13,pp 1065-1067,May 1974

28. Loos, G. C., and Hogge, C. B., "Turbulence in the Upper Atmosphere and Isoplanatism", Applied Optics, v. 18, pp 2658-2659, August 1979.

29. Fried, D. L., "Anisoplanatism in Adaptive Optics", Agard Conference Proceedings, no. 300, p 46-1, 1980.

30. Loos, G. C., and Hogge, C. B., "Turbulence in the Upper Atmosphere and Isoplanatism", Applied Optics, v. 18, p 2659, August 1979.

31. Hogge, C. B., "Adaptive Optics in High Energy Laser Systems", Adaptive Optics and Short Wavelength Sources, Physics of Quantum Electronics series, v. 6, pp 82-84, 1978.

32. Hufnagel, R. E., "Variations of Atmospheric Turbulence", Digest of Technical Papers, Topical Meeting on Optical Propagation Through Turbulence, Optical Society of America, 1974.

33. Butts, R. R., and Hogge, C. B., "Point Ahead Limitations on Adaptive Optics for Ground to Space Transmission", Laser Digest, AFWL-TR-79-46, p 65, May 1979.

34. Yura, H. T., "Atmospheric Turbulence Induced Laser Spread", Applied Optics, v. 10, p 2771, December 1971.

35. Fried, D. L., "Limiting Resolution Looking Down Through the Atmosphere", Journal of the Optical Society of America, v. 56, pp 1380-1384, October 1966.

36. Forgham, J. L., Shea, R. F., and Townsend, S. S. "Unambiguous Zernike Polynomial Coefficients", Laser Digest, AFWL-TR-79-46, pp 34-38, May 1979.

37. Personal communication with Capt. A. Boye, AFWL, Albuquerque, NM.

38. Optical Sciences Report No. TR-249, Isoplanatism Dependence of a Ground to Space Laser Transmitter with Adaptive Optics by D. L. Fried, 1977.

39. Optical Sciences Report No. TR-249, Isoplanatism Dependence of a Ground to Space Laser Transmitter with Adaptive Optics by D. L. Fried, 1977.

INITIAL DISTRIBUTION LIST

		No. Copies
1.	Defense Technical Information Center Cameron Station Alexandria, Virginia, 22314	2
2.	Library Code 0142 Naval Postgraduate School Monterey, California, 93943	2
3.	Professor Allen E. Fuhs, Code 67Fu Department of Aeronautics Naval Postgraduate School Monterey, California, 93943	2
4.	Dr. Fred Raymond Code 9110 Naval Research Laboratory 4555 Overlook Ave. SW Washington D.C. 20375	2
5.	Dr. C. B. Hogge Air Force Weapons Laboratory Kirtland AFB, NM, 87117	2
6.	LCDR Bert Homan LEAPS Division Air Force Weapons Laboratory Kirtland AFB, NM, 87117	2
7.	LT Joel S. Morrow 13634 Picarsa Dr Jacksonville Beach, Florida,32225	2